We are IntechOpen, the world's leading publisher of Open Access books Built by scientists, for scientists

6,300

Open access books available

172,000

International authors and editors

190M

Downloads

Our authors are among the

154

Countries delivered to

TOP 1%

most cited scientists

12.2%

Contributors from top 500 universities

WEB OF SCIENCE™

Selection of our books indexed in the Book Citation Index
in Web of Science™ Core Collection (BKCI)

Interested in publishing with us?
Contact book.department@intechopen.com

Numbers displayed above are based on latest data collected.
For more information visit www.intechopen.com

Robust Control of Nonlinear Time-Delay Systems via Takagi-Sugeno Fuzzy Models

Hamdi Gassara^{1,2}, Ahmed El Hajjaji¹ and Mohamed Chaabane³

¹*Modeling, Information, and Systems Laboratory, University of Picardie
Jules Verne, Amiens 80000,*

²*Department of Electrical Engineering, Unit of Control of Industrial Process,
National School of Engineering, University of Sfax, Sfax 3038*

³*Automatic control at National School of Engineers of Sfax (ENIS)*

¹*France*

^{2,3}*Tunisia*

1. Introduction

Robust control theory is an interdisciplinary branch of engineering and applied mathematics literature. Since its introduction in 1980's, it has grown to become a major scientific domain. For example, it gained a foothold in Economics in the late 1990 and has seen increasing numbers of Economic applications in the past few years. This theory aims to design a controller which guarantees closed-loop stability and performances of systems in the presence of system uncertainty. In practice, the uncertainty can include modelling errors, parametric variations and external disturbance. Many results have been presented for robust control of linear systems. However, most real physical systems are nonlinear in nature and usually subject to uncertainties. In this case, the linear dynamic systems are not powerful to describe these practical systems. So, it is important to design robust control of nonlinear models. In this context, different techniques have been proposed in the literature (Input-Output linearization technique, backstepping technique, Variable Structure Control (VSC) technique, ...).

These two last decades, fuzzy model control has been extensively studied; see (Zhang & Heng, 2002)-(Chadli & ElHajjaji, 2006)-(Kim & Lee, 2000)-(Boukas & ElHajjaji, 2006) and the references therein because T-S fuzzy model can provide an effective representation of complex nonlinear systems. On the other hand, time-delay are often occurs in various practical control systems, such as transportation systems, communication systems, chemical processing systems, environmental systems and power systems. It is well known that the existence of delays may deteriorate the performances of the system and can be a source of instability. As a consequence, the T-S fuzzy model has been extended to deal with nonlinear systems with time-delay. The existing results of stability and stabilization criteria for this class of T-S fuzzy systems can be classified into two types: delay-independent, which are applicable to delay of arbitrary size (Cao & Frank, 2000)-(Park et al., 2003)-(Chen & Liu, 2005b), and delay-dependent, which include information on the size of delays, (Li et al., 2004) - (Chen & Liu, 2005a). It is generally recognized that delay-dependent results are usually less conservative than delay-independent ones, especially when the size of delay

is small. We notice that all the results of analysis and synthesis delay-dependent methods cited previously are based on a single LKF that bring conservativeness in establishing the stability and stabilization test. Moreover, the model transformation, the conservative inequalities and the so-called Moon's inequality (Moon et al., 2001) for bounding cross terms used in these methods also bring conservativeness. Recently, in order to reduce conservatism, the weighting matrix technique was proposed originally by He and al. in (He et al., 2004)-(He et al., 2007). These works studied the stability of linear systems with time-varying delay. More recently, Huai-Ning et al. (Wu & Li, 2007) treated the problem of stabilization via PDC (Parallel Distributed Compensation) control by employing a fuzzy LKF combining the introduction of free weighting matrices which improves existing ones in (Li et al., 2004) - (Chen & Liu, 2005a) without imposing any bounding techniques on some cross product terms. In general, the disadvantage of this new approach (Wu & Li, 2007) lies in that the delay-dependent stabilization conditions presented involve three tuning parameters. Chen et al. in (Chen et al., 2007) and in (Chen & Liu, 2005a) have proposed delay-dependent stabilization conditions of uncertain T-S fuzzy systems. The inconvenience in these works is that the time-delay must be constant. The designing of observer-based fuzzy control and the introduction of performance with guaranteed cost for T-S with input delay have discussed in (Chen, Lin, Liu & Tong, 2008) and (Chen, Liu, Tang & Lin, 2008), respectively.

In this chapter, we study the asymptotic stabilization of uncertain T-S fuzzy systems with time-varying delay. We focus on the delay-dependent stabilization synthesis based on the PDC scheme (Wang et al., 1996). Different from the methods currently found in the literature (Wu & Li, 2007)-(Chen et al., 2007), our method does not need any transformation in the LKF, and thus, avoids the restriction resulting from them. Our new approach improves the results in (Li et al., 2004)-(Guan & Chen, 2004)-(Chen & Liu, 2005a)-(Wu & Li, 2007) for three great main aspects. The first one concerns the reduction of conservatism. The second one, the reduction of the number of LMI conditions, which reduce computational efforts. The third one, the delay-dependent stabilization conditions presented involve a single fixed parameter. This new approach also improves the work of B. Chen et al. in (Chen et al., 2007) by establishing new delay-dependent stabilization conditions of uncertain T-S fuzzy systems with time varying delay. The rest of this chapter is organized as follows. In section 2, we give the description of uncertain T-S fuzzy model with time varying delay. We also present the fuzzy control design law based on PDC structure. New delay dependent stabilization conditions are established in section 3. In section 4, numerical examples are given to demonstrate the effectiveness and the benefits of the proposed method. Some conclusions are drawn in section 5.

Notation: $\mathbb{R}^n$ denotes the n -dimensional Euclidean space. The notation $P > 0$ means that P is symmetric and positive definite. $W + W^T$ is denoted as $W + (*)$ for simplicity. In symmetric bloc matrices, we use $*$ as an ellipsis for terms that are induced by symmetry.

2. Problem formulation

Consider a nonlinear system with state-delay which could be represented by a T-S fuzzy time-delay model described by

Plant Rule $i(i = 1, 2, \dots, r)$: If θ_1 is μ_{i1} and $\dots$ and θ_p is μ_{ip} THEN

$$\begin{aligned}\dot{x}(t) &= (A_i + \Delta A_i)x(t) + (A_{\tau i} + \Delta A_{\tau i})x(t - \tau(t)) + (B_i + \Delta B_i)u(t) \\ x(t) &= \psi(t), t \in [-\bar{\tau}, 0],\end{aligned}\tag{1}$$

where $\theta_j(x(t))$ and $\mu_{ij}(i = 1, \dots, r, j = 1, \dots, p)$ are respectively the premise variables and the fuzzy sets; $\psi(t)$ is the initial conditions; $x(t) \in \mathbb{R}^n$ is the state; $u(t) \in \mathbb{R}^m$ is the control input; r is the number of IF-THEN rules; the time delay, $\tau(t)$, is a time-varying continuous function that satisfies

$$0 \leq \tau(t) \leq \bar{\tau}, \dot{\tau}(t) \leq \beta \quad (2)$$

The parametric uncertainties $\Delta A_i, \Delta A_{\tau i}, \Delta B_i$ are time-varying matrices that are defined as follows

$$\Delta A_i = M_{Ai}F_i(t)E_{Ai}, \Delta A_{\tau i} = M_{A\tau i}F_i(t)E_{A\tau i}, \Delta B_i = M_{Bi}F_i(t)E_{Bi} \quad (3)$$

where $M_{Ai}, M_{A\tau i}, M_{Bi}, E_{Ai}, E_{A\tau i}, E_{Bi}$ are known constant matrices and $F_i(t)$ is an unknown matrix function with the property

$$F_i(t)^T F_i(t) \leq I \quad (4)$$

Let $\bar{A}_i = A_i + \Delta A_i$; $\bar{A}_{\tau i} = A_{\tau i} + \Delta A_{\tau i}$; $\bar{B}_i = B_i + \Delta B_i$

By using the common used center-average defuzzifier, product inference and singleton fuzzifier, the T-S fuzzy systems can be inferred as

$$\dot{x}(t) = \sum_{i=1}^r h_i(\theta(x(t))) [\bar{A}_i x(t) + \bar{A}_{\tau i} x(t - \tau(t)) + \bar{B}_i u(t)] \quad (5)$$

where $\theta(x(t)) = [\theta_1(x(t)), \dots, \theta_p(x(t))]$ and $v_i(\theta(x(t))) : \mathbb{R}^p \rightarrow [0, 1], i = 1, \dots, r$, is the membership function of the system with respect to the i th plan rule. Denote $h_i(\theta(x(t))) = v_i(\theta(x(t))) / \sum_{i=1}^r v_i(\theta(x(t)))$. It is obvious that

$$h_i(\theta(x(t))) \geq 0 \text{ and } \sum_{i=1}^r h_i(\theta(x(t))) = 1$$

the design of state feedback stabilizing fuzzy controllers for fuzzy system (5) is based on the Parallel Distributed Compensation.

Controller Rule $i(i = 1, 2, \dots, r)$: If θ_1 is μ_{i1} and $\dots$ and θ_p is μ_{ip} THEN

$$u(t) = K_i x(t) \quad (6)$$

The overall state feedback control law is represented by

$$u(t) = \sum_{i=1}^r h_i(\theta(x(t))) K_i x(t) \quad (7)$$

In the sequel, for brevity we use h_i to denote $h_i(\theta(x(t)))$. Combining (5) with (7), the closed-loop fuzzy system can be expressed as follows

$$\dot{x}(t) = \sum_{i=1}^r \sum_{j=1}^r h_i h_j [\hat{A}_{ij} x(t) + \bar{A}_{\tau i} x(t - \tau(t))] \quad (8)$$

with $\hat{A}_{ij} = \bar{A}_i + \bar{B}_i K_j$

In order to obtain the main results in this chapter, the following lemmas are needed

Lemma 1. (Xie & DeSouza, 1992)-(Oudghiri et al., 2007) (Guerra et al., 2006) Considering $\Pi < 0$ a matrix X and a scalar λ , the following holds

$$X^T \Pi X \leq -2\lambda X - \lambda^2 \Pi^{-1} \quad (9)$$

Lemma 2. (Wang et al., 1992) Given matrices $M, E, F(t)$ with compatible dimensions and $F(t)$ satisfying $F(t)^T F(t) \leq I$.

Then, the following inequalities hold for any $\epsilon > 0$

$$MF(t)E + E^T F(t)^T M^T \leq \epsilon MM^T + \epsilon^{-1} E^T E \quad (10)$$

3. Main results

3.1 Time-delay dependent stability conditions

First, we derive the stability condition for unforced system (5), that is

$$\dot{x}(t) = \sum_{i=1}^r h_i [\bar{A}_i x(t) + \bar{A}_{\tau i} x(t - \tau(t))] \quad (11)$$

Theorem 1. System (11) is asymptotically stable, if there exist some matrices $P > 0, S > 0, Z > 0, Y$ and T satisfying the following LMIs for $i = 1, 2, \dots, r$

$$\begin{bmatrix} \varphi_i + \epsilon_{Ai} E_{Ai}^T E_{Ai} & PA_{\tau i} - Y + T^T & A_{\tau i}^T Z & -Y & PM_{Ai} & PM_{A\tau i} \\ * & -(1 - \beta)S - T - T^T + \epsilon_{A\tau i} E_{\tau i}^T E_{\tau i} & A_{\tau i}^T Z & -T & 0 & \\ * & * & -\frac{1}{\tau} Z & 0 & ZM_{Ai} & ZM_{A\tau i} \\ * & * & * & -\frac{1}{\tau} Z & 0 & \\ * & * & * & * & -\epsilon_{Ai} I & 0 \\ * & * & * & * & * & -\epsilon_{A\tau i} I \end{bmatrix} < 0 \quad (12)$$

where $\varphi_i = PA_i + A_i^T P + S + Y + Y^T$.

Proof 1. Choose the LKF as

$$V(x(t)) = x(t)^T P x(t) + \int_{t-\tau(t)}^t x(\alpha)^T S x(\alpha) d\alpha + \int_{-\bar{\tau}}^0 \int_{t+\sigma}^t \dot{x}(\alpha)^T Z \dot{x}(\alpha) d\alpha d\sigma \quad (13)$$

the time derivative of this LKF (13) along the trajectory of system (11) is computed as

$$\begin{aligned} \dot{V}(x(t)) &= 2x(t)^T P \dot{x}(t) + x(t)^T S x(t) - (1 - \dot{\tau}(t)) x(t - \tau(t))^T S x(t - \tau(t)) \\ &\quad + \bar{\tau} \dot{x}(t)^T Z \dot{x}(t) - \int_{t-\bar{\tau}}^t \dot{x}(s)^T Z \dot{x}(s) ds \end{aligned} \quad (14)$$

Taking into account the Newton-Leibniz formula

$$x(t - \tau(t)) = x(t) - \int_{t-\tau(t)}^t \dot{x}(s) ds \quad (15)$$

We obtain equation (16)

$$\begin{aligned}
\dot{V}(x(t)) = & \sum_{i=1}^r h_i [2x(t)^T P \bar{A}_i x(t) + 2x(t)^T P \bar{A}_{\tau i} x(t - \tau(t))] \\
& + x(t)^T S x(t) - (1 - \beta) x(t - \tau(t))^T S x(t - \tau(t)) \\
& + \bar{\tau} \dot{x}(t)^T Z \dot{x}(t) - \int_{t-\bar{\tau}}^t \dot{x}(s)^T Z \dot{x}(s) ds \\
& + 2[x(t)^T Y + x(t - \tau(t))^T T] \times [x(t) - x(t - \tau(t)) - \int_{t-\tau(t)}^t \dot{x}(s) ds] \quad (16)
\end{aligned}$$

As pointed out in (Chen & Liu, 2005a)

$$\dot{x}(t)^T Z \dot{x}(t) \leq \sum_{i=1}^r h_i \eta(t)^T \begin{bmatrix} \bar{A}_i^T Z \bar{A}_i & \bar{A}_i^T Z \bar{A}_{\tau i} \\ \bar{A}_{\tau i}^T Z \bar{A}_i & \bar{A}_{\tau i}^T Z \bar{A}_{\tau i} \end{bmatrix} \eta(t) \quad (17)$$

where $\eta(t)^T = [x(t)^T, x(t - \tau(t))^T]$.

Allowing $W^T = [Y^T, T^T]$, we obtain equation (18)

$$\begin{aligned}
\dot{V}(x(t)) \leq & \sum_{i=1}^r h_i \eta(t)^T [\tilde{\Phi}_i + \bar{\tau} W Z^{-1} W^T] \eta(t) \\
& - \int_{t-\tau(t)}^t [\eta^T(t) W + \dot{x}(s)^T Z] Z^{-1} [\eta^T(t) W + \dot{x}(s)^T Z]^T ds \quad (18)
\end{aligned}$$

where

$$\tilde{\Phi}_i = \begin{bmatrix} P \bar{A}_i + \bar{A}_i^T P + S + \bar{\tau} \bar{A}_i^T Z \bar{A}_i + Y + Y^T & P \bar{A}_{\tau i} + \bar{\tau} \bar{A}_i^T Z \bar{A}_{\tau i} - Y + T^T \\ * & -(1 - \beta) S + \bar{\tau} \bar{A}_{\tau i}^T Z \bar{A}_{\tau i} - T - T^T \end{bmatrix} \quad (19)$$

By applying Schur complement $\tilde{\Phi}_i + \bar{\tau} W Z^{-1} W^T < 0$ is equivalent to

$$\tilde{\Phi}_i = \begin{bmatrix} \bar{\varphi}_i & P \bar{A}_{\tau i} - Y + T^T & \bar{A}_i^T Z & -Y \\ * & -(1 - \beta) S - T - T^T & \bar{A}_{\tau i}^T Z & -T \\ * & * & -\frac{1}{\bar{\tau}} Z & 0 \\ * & * & * & -\frac{1}{\bar{\tau}} Z \end{bmatrix} < 0$$

The uncertain part is represented as follows

$$\begin{aligned}
\Delta \tilde{\Phi}_i = & \begin{bmatrix} P \Delta A_i + \Delta A_i^T P & P \Delta A_{\tau i} & \Delta A_i^T Z & 0 \\ * & 0 & \Delta A_{\tau i}^T Z & 0 \\ * & * & 0 & 0 \\ * & * & * & 0 \end{bmatrix} \\
= & \begin{bmatrix} P M_{Ai} \\ 0 \\ Z M_{Ai} \\ 0 \end{bmatrix} F(t) \begin{bmatrix} E_{Ai} & 0 & 0 & 0 \end{bmatrix} + (*) + \begin{bmatrix} P M_{A\tau i} \\ 0 \\ Z M_{A\tau i} \\ 0 \end{bmatrix} F(t) \begin{bmatrix} 0 & E_{A\tau i} & 0 & 0 \end{bmatrix} + (*) \quad (20)
\end{aligned}$$

By applying lemma 2, we obtain

$$\begin{aligned} \Delta \bar{\Phi}_i \leq & \epsilon_{Ai}^{-1} \begin{bmatrix} PM_{Ai} \\ 0 \\ ZM_{Ai} \\ 0 \end{bmatrix} [M_{Ai}^T P \ 0 \ M_{Ai}^T Z \ 0] + \epsilon_{Ai} \begin{bmatrix} E_{Ai}^T \\ 0 \\ 0 \\ 0 \end{bmatrix} [E_{Ai} \ 0 \ 0 \ 0] \\ & + \epsilon_{A\tau i}^{-1} \begin{bmatrix} PM_{A\tau i} \\ 0 \\ ZM_{A\tau i} \\ 0 \end{bmatrix} [M_{A\tau i}^T P \ 0 \ M_{A\tau i}^T Z \ 0] + \epsilon_{A\tau i} \begin{bmatrix} 0 \\ E_{A\tau i}^T \\ 0 \\ 0 \end{bmatrix} [0 \ E_{A\tau i} \ 0 \ 0] \end{aligned} \quad (21)$$

where ϵ_{Ai} and $\epsilon_{A\tau i}$ are some positive scalars.

By using Schur complement, we obtain theorem 1.

3.2 Time-delay dependent stabilization conditions

Theorem 2. System (8) is asymptotically stable if there exist some matrices $P > 0$, $S > 0$, $Z > 0$, Y , T satisfying the following LMIs for $i, j = 1, 2, \dots, r$ and $i \leq j$

$$\bar{\Phi}_{ij} + \bar{\Phi}_{ji} \leq 0 \quad (22)$$

where $\bar{\Phi}_{ji}$ is given by

$$\bar{\Phi}_{ij} = \begin{bmatrix} P\hat{A}_{ij} + \hat{A}_{ij}^T P + S + Y + Y^T & P\bar{A}_{\tau i} - Y + T^T & \hat{A}_{ij}^T Z & -Y \\ * & -(1-\beta)S - T - T^T & \bar{A}_{\tau i}^T Z & -T \\ * & * & -\frac{1}{\tau}Z & 0 \\ * & * & * & -\frac{1}{\tau}Z \end{bmatrix} \quad (23)$$

Proof 2. As pointed out in (Chen & Liu, 2005a), the following inequality is verified.

$$\dot{x}(t)^T Z \dot{x}(t) \leq \sum_{i=1}^r \sum_{j=1}^r h_i h_j \eta(t)^T \begin{bmatrix} \frac{(\hat{A}_{ij} + \hat{A}_{ji})^T}{2} Z \frac{(\hat{A}_{ij} + \hat{A}_{ji})}{2} & \frac{(\hat{A}_{ij} + \hat{A}_{ji})^T}{2} Z \frac{(\bar{A}_{\tau i} + \bar{A}_{\tau j})}{2} \\ \frac{(\bar{A}_{\tau i} + \bar{A}_{\tau j})^T}{2} Z \frac{(\hat{A}_{ij} + \hat{A}_{ji})}{2} & \frac{(\bar{A}_{\tau i} + \bar{A}_{\tau j})^T}{2} Z \frac{(\bar{A}_{\tau i} + \bar{A}_{\tau j})}{2} \end{bmatrix} \eta(t) \quad (24)$$

Following a similar development to that for theorem 1, we obtain

$$\begin{aligned} \dot{V}(x(t)) \leq & \sum_{i=1}^r \sum_{j=1}^r h_i h_j \eta(t)^T [\bar{\Phi}_{ij} + \tau W Z^{-1} W^T] \eta(t) \\ & - \int_{t-\tau(t)}^t [\eta(t)^T W + \dot{x}(s)^T Z] Z^{-1} [\eta(t)^T W + \dot{x}(s)^T Z]^T ds \end{aligned} \quad (25)$$

where $\bar{\Phi}_{ij}$ is given by

$$\bar{\Phi}_{ij} = \begin{bmatrix} P\hat{A}_{ij} + \hat{A}_{ij}^T P + S & P\bar{A}_{\tau i} + \bar{\tau} \frac{(\hat{A}_{ij} + \hat{A}_{ji})^T}{2} Z \frac{(\bar{A}_{\tau i} + \bar{A}_{\tau j})}{2} \\ + \bar{\tau} \frac{(\hat{A}_{ij} + \hat{A}_{ji})^T}{2} Z \frac{(\hat{A}_{ij} + \hat{A}_{ji})}{2} + Y + Y^T & -Y + T^T \\ * & -(1-\beta)S + \bar{\tau} \frac{(\bar{A}_{\tau i} + \bar{A}_{\tau j})^T}{2} Z \frac{(\bar{A}_{\tau i} + \bar{A}_{\tau j})}{2} \\ & -T - T^T \end{bmatrix} \quad (26)$$

By applying Schur complement $\sum_{i=1}^r \sum_{j=1}^r h_i h_j \tilde{\Phi}_{ij} + \bar{\tau} W Z^{-1} W^T < 0$ is equivalent to

$$\begin{aligned} \sum_{i=1}^r \sum_{j=1}^r h_i h_j \hat{\Phi}_{ij} &= \frac{1}{2} \sum_{i=1}^r \sum_{j=1}^r h_i h_j (\hat{\Phi}_{ij} + \hat{\Phi}_{ji}) \\ &= \frac{1}{2} \sum_{i=1}^r \sum_{j=1}^r h_i h_j (\tilde{\Phi}_{ij} + \tilde{\Phi}_{ji}) < 0 \end{aligned} \quad (27)$$

where $\hat{\Phi}_{ij}$ is given by

$$\hat{\Phi}_{ij} = \begin{bmatrix} P\hat{A}_{ij} + \hat{A}_{ij}^T P + S + Y + Y^T & P\bar{A}_{\tau i} - Y + T^T & \frac{(\hat{A}_{ij} + \hat{A}_{ji})^T}{2} Z & -Y \\ * & -(1 - \beta)S - T - T^T & \frac{(\bar{A}_{\tau i} + \bar{A}_{\tau j})^T}{2} Z & -T \\ * & * & -\frac{1}{\bar{\tau}} Z & 0 \\ * & * & * & -\frac{1}{\bar{\tau}} Z \end{bmatrix} \quad (28)$$

Therefore, we get $\dot{V}(x(t)) \leq 0$.

Our objective is to transform the conditions in theorem 2 in LMI terms which can be easily solved using existing solvers such as LMI TOOLBOX in the Matlab software.

Theorem 3. For a given positive number λ . System (8) is asymptotically stable if there exist some matrices $P > 0$, $S > 0$, $Z > 0$, Y , T and N_i as well as positives scalars ϵ_{Aij} , $\epsilon_{A\tau ij}$, ϵ_{Bij} , ϵ_{Ci} , $\epsilon_{C\tau i}$, ϵ_{Di} satisfying the following LMIs for $i, j = 1, 2, \dots, r$ and $i \leq j$

$$\Xi_{ij} + \Xi_{ji} \leq 0 \quad (29)$$

where Ξ_{ij} is given by

$$\Xi_{ij} = \begin{bmatrix} \begin{bmatrix} \xi_{ij} + \epsilon_{Aij} M_{Ai} M_{Ai}^T \\ + \epsilon_{Bij} M_{Bi} M_{Bi}^T \end{bmatrix} & P A_{\tau i}^T - Y + T^T & A_i P + B_i N_j & -Y \\ * & \begin{bmatrix} -(1 - \beta)S - T - T^T \\ + \epsilon_{A\tau ii} M_{A\tau ii} M_{A\tau ii}^T \end{bmatrix} & A_{\tau i} P & \\ * & * & \frac{1}{\bar{\tau}} (-2\lambda P + \lambda^2 Z) & 0 \\ * & * & * & -\frac{1}{\bar{\tau}} Z \\ * & * & * & * \\ * & * & * & * \end{bmatrix} \quad (30)$$

$$\begin{bmatrix} P E_{Ai}^T & N_j^T E_{Bi}^T & P E_{A\tau i}^T \\ -T & 0 & 0 \\ P E_{Ai}^T & N_j^T E_{Bi}^T & P E_{A\tau i}^T \\ 0 & 0 & 0 \\ -\epsilon_{Aij} I & 0 & 0 \\ * & -\epsilon_{Bij} I & 0 \\ * & * & -\epsilon_{A\tau ij} I \end{bmatrix}$$

in which $\xi_{ij} = PA_i^T + N_j^T B_i^T + A_i P + B_i N_j + S + Y + Y^T$. If this is the case, the K_i local feedback gains are given by

$$K_i = N_i P^{-1}, i = 1, 2, \dots, r \quad (31)$$

Proof 3. Starting with pre-and post multiplying (22) by $\text{diag}[I, I, Z^{-1}P, I]$ and its transpose, we get

$$\Xi_{ij}^1 + \Xi_{ji}^1 \leq 0, \quad 1 \leq i \leq j \leq r \quad (32)$$

where

$$\Xi_{ij}^1 = \begin{bmatrix} P\hat{A}_{ij} + \hat{A}_{ij}^T P + S + Y + Y^T & P\bar{A}_{\tau i} - Y + T^T & \hat{A}_{ij}^T P & -Y \\ * & -(1-\beta)S - T - T^T & \bar{A}_{\tau i}^T P & -T \\ * & * & -\frac{1}{\tau}PZ^{-1}P & 0 \\ * & * & * & -\frac{1}{\tau}Z \end{bmatrix} \quad (33)$$

As pointed out by Wu et al. (Wu et al., 2004), if we just consider the stabilization condition, we can replace $\hat{A}_{ij}$, $A_{\tau i}$ with $\hat{A}_{ij}^T$ and $A_{\tau i}^T$, respectively, in (33).

Assuming $N_j = K_j P$, we get

$$\Xi_{ij}^2 + \Xi_{ji}^2 \leq 0, \quad 1 \leq i \leq j \leq r \quad (34)$$

$$\Xi_{ij}^2 = \begin{bmatrix} \bar{\xi}_{ij} & P\bar{A}_{\tau i}^T - Y + T^T & \bar{A}_i P + \bar{B}_i N_j & -Y \\ * & \begin{bmatrix} -(1-\beta)S \\ -T - T^T \end{bmatrix} & \bar{A}_{\tau i} P & -T \\ * & * & -\frac{1}{\tau}PZ^{-1}P & 0 \\ * & * & * & -\frac{1}{\tau}Z \end{bmatrix} \quad (35)$$

It follows from lemma 1 that

$$-PZ^{-1}P \leq -2\lambda P + \lambda^2 Z \quad (36)$$

We obtain

$$\Xi_{ij}^3 + \Xi_{ji}^3 \leq 0, \quad 1 \leq i \leq j \leq r \quad (37)$$

where

$$\Xi_{ij}^3 = \begin{bmatrix} \bar{\xi}_{ij} & P\bar{A}_{\tau i}^T - Y + T^T & \bar{A}_i P + \bar{B}_i N_j & -Y \\ * & \begin{bmatrix} -(1-\beta)S \\ -T - T^T \end{bmatrix} & \bar{A}_{\tau i} P & -T \\ * & * & \begin{bmatrix} \frac{1}{\tau}(-2\lambda P \\ +\lambda^2 Z) \end{bmatrix} & 0 \\ * & * & * & -\frac{1}{\tau}Z \end{bmatrix} \quad (38)$$

The uncertain part is given by

$$\begin{aligned} \Delta \bar{\Xi}_{ij} &= \begin{bmatrix} P\Delta A_i^T + N_j^T \Delta B_i^T + \Delta A_i P + \Delta B_i N_j & P\Delta A_{\tau i}^T & \Delta A_i P + \Delta B_i N_j & 0 \\ * & 0 & \Delta A_{\tau i} P & 0 \\ * & * & 0 & 0 \\ * & * & * & 0 \end{bmatrix} \\ &= \begin{bmatrix} M_{Ai} \\ 0_{3 \times 1} \end{bmatrix} F(t) \begin{bmatrix} E_{Ai} P & 0 & E_{Ai} P & 0 \end{bmatrix} + (*) \\ &\quad + \begin{bmatrix} M_{Bi} \\ 0_{3 \times 1} \end{bmatrix} F(t) \begin{bmatrix} E_{Bi} N_j & 0 & E_{Bi} N_j & 0 \end{bmatrix} + (*) \\ &\quad + \begin{bmatrix} 0 \\ M_{A\tau i} \\ 0_{2 \times 1} \end{bmatrix} F(t) \begin{bmatrix} E_{A\tau i} P & 0 & E_{A\tau i} P & 0 \end{bmatrix} + (*) \end{aligned} \quad (39)$$

By using lemma 2, we obtain

$$\begin{aligned} \Delta \bar{\Xi}_{ij} &\leq \epsilon_{Aij} \begin{bmatrix} M_{Ai} \\ 0_{3 \times 1} \end{bmatrix} \begin{bmatrix} M_{Ai}^T & 0_{1 \times 3} \end{bmatrix} + \epsilon_{Aij}^{-1} \begin{bmatrix} P E_{Ai}^T \\ 0 \\ P E_{Ai}^T \\ 0 \end{bmatrix} \begin{bmatrix} E_i P & 0 & E_i P & 0 \end{bmatrix} \\ &\quad + \epsilon_{Bij} \begin{bmatrix} M_{Bi} \\ 0_{3 \times 1} \end{bmatrix} \begin{bmatrix} M_{Bi}^T & 0_{1 \times 3} \end{bmatrix} + \epsilon_{Bij}^{-1} \begin{bmatrix} N_j^T E_{Bi}^T \\ 0 \\ N_j^T E_{Bi}^T \\ 0 \end{bmatrix} \begin{bmatrix} E_{Bi} N_j & 0 & E_{Bi} N_j & 0 \end{bmatrix} \\ &\quad + \epsilon_{A\tau ij} \begin{bmatrix} 0 \\ M_{A\tau i} \\ 0_{2 \times 1} \end{bmatrix} \begin{bmatrix} 0 & M_{A\tau i}^T & 0_{1 \times 2} \end{bmatrix} + \epsilon_{A\tau ij}^{-1} \begin{bmatrix} P E_{A\tau i}^T \\ 0 \\ P E_{A\tau i}^T \\ 0 \end{bmatrix} \begin{bmatrix} E_{A\tau i} P & 0 & E_{A\tau i} P & 0 \end{bmatrix} \end{aligned} \quad (40)$$

where ϵ_{Aij} , $\epsilon_{A\tau ij}$ and ϵ_{Bij} are some positive scalars.

By applying Schur complement and lemma 2, we obtain theorem 3.

Remark 1. It is noticed that (Wu & Li, 2007) and theorem (3) contain, respectively, $r^3 + r^3(r-1)$ and $\frac{1}{2}r(r+1)$ LMIs. This reduces the computational complexity. Moreover, it is easy to see that the requirements of $\beta < 1$ are removed in our result due to the introduction of variable T .

Remark 2. It is noted that Wu et al. in (Wu & Li, 2007) have presented a new approach to delay-dependent stabilization for continuous-time fuzzy systems with time varying delay. The disadvantages of this new approach is that the LMIs presented involve three tuning parameters. However, only one tuning parameter is involved in our approach.

Remark 3. Our method provides a less conservative result than other results which have been recently proposed (Wu & Li, 2007), (Chen & Liu, 2005a), (Guan & Chen, 2004). In next paragraph, a numerical example is given to demonstrate numerically this point.

4. Illustrative examples

In this section, three examples are used to illustrate the effectiveness and the merits of the proposed results. The first example is given to compare our result with the existing one in the case of constant delay and time-varying delay.

4.1 Example 1

Consider the following T-S fuzzy model

$$\dot{x}(t) = \sum_{i=1}^2 h_i(x_1(t))[(A_i + \Delta A_i)x(t) + (A_{\tau i} + \Delta A_{\tau i})x(t - \tau(t)) + B_i u(t)] \tag{41}$$

where

$$A_1 = \begin{bmatrix} 0 & 0.6 \\ 0 & 1 \end{bmatrix}, A_2 = \begin{bmatrix} 1 & 0 \\ 1 & 0 \end{bmatrix}, A_{\tau 1} = \begin{bmatrix} 0.5 & 0.9 \\ 0 & 2 \end{bmatrix}, A_{\tau 2} = \begin{bmatrix} 0.9 & 0 \\ 1 & 1.6 \end{bmatrix}$$

$$B_1 = B_2 = \begin{bmatrix} 1 \\ 1 \end{bmatrix}$$

$$\Delta A_i = MF(t)E_i, \Delta A_{\tau i} = MF(t)E_{\tau i}$$

$$M = \begin{bmatrix} -0.03 & 0 \\ 0 & 0.03 \end{bmatrix}$$

$$E_1 = E_2 = \begin{bmatrix} -0.15 & 0.2 \\ 0 & 0.04 \end{bmatrix}$$

$$E_{\tau 1} = E_{\tau 2} = \begin{bmatrix} -0.05 & -0.35 \\ 0.08 & -0.45 \end{bmatrix}$$

The membership functions are defined by

$$\begin{aligned} h_1(x_1(t)) &= \frac{1}{1 + \exp(-2x_1(t))} \\ h_2(x_1(t)) &= 1 - h_1(x_1(t)) \end{aligned} \tag{42}$$

For the case of delay being constant and unknown and no uncertainties ($\Delta A_i = 0, \Delta A_{\tau i} = 0$), the existing delay-dependent approaches are used to design the fuzzy controllers. Based on theorem 3, for $\lambda = 5$, the largest delay is computed to be $\bar{\tau} = 0.4909$ such that system (41) is asymptotically stable. Based on the results obtained in (Wu & Li, 2007), we get this table

Methods	Maximum allowed τ
Theorem of Chen and Liu (Chen & Liu, 2005a)	0.1524
Theorem of Guan and Chen (Guan & Chen, 2004)	0.2302
Theorem of Wu and Li (Wu & Li, 2007)	0.2664
Theorem 3	0.4909

Table 1. Comparison Among Various Delay-Dependent Stabilization Methods

It appears from this table that our result improves the existing ones. Letting $\bar{\tau} = 0.4909$, the state-feedback gain matrices are

$$K_1 = \begin{bmatrix} 5.5780 & -16.4347 \end{bmatrix}, K_2 = \begin{bmatrix} 4.0442 & -15.4370 \end{bmatrix}$$

Fig 1 shows the control results for system (41) with constant time-delay via fuzzy controller (7) with the previous gain matrices under the initial condition $x(t) = \begin{bmatrix} 2 & 0 \end{bmatrix}^T, t \in [-0.4909 \ 0]$.

Fig. 1. Control results for system (41) without uncertainties and with constant time delay $\tau = 0.4909$.

It is clear that the designed fuzzy controller can stabilize this system.

For the case of $\Delta A_i \neq 0, \Delta A_{\tau i} \neq 0$ and constant delay, the approaches in (Guan & Chen, 2004) (Wu & Li, 2007) (Lin et al., 2006) cannot be used to design feedback controllers as the system contains uncertainties. The method in (Chen & Liu, 2005b) and theorem 3 with $\lambda = 5$ can be used to design the fuzzy controllers. The corresponding results are listed below.

Methods	Maximum allowed τ
Theorem of Chen and Liu (Chen & Liu, 2005a)	0.1498
Theorem 3	0.4770

Table 2. Comparison Among Various Delay-Dependent Stabilization Methods With uncertainties

It appears from Table 2 that our result improves the existing ones in the case of uncertain T-S fuzzy model with constant time-delay.

For the case of uncertain T-S fuzzy model with time-varying delay, the approaches proposed in (Guan & Chen, 2004) (Chen & Liu, 2005a) (Wu & Li, 2007) (Chen et al., 2007) and (Lin et al., 2006) cannot be used to design feedback controllers as the system contains uncertainties and time-varying delay. By using theorem 3 with the choice of $\lambda = 5, \tau(t) = 0.25 + 0.15 \sin(t) (\bar{\tau} = 0.4, \beta = 0.15)$, we can obtain the following state-feedback gain matrices:

$$K_1 = \begin{bmatrix} 4.7478 & -13.5217 \end{bmatrix}, K_2 = \begin{bmatrix} 3.1438 & -13.2255 \end{bmatrix}$$

The simulation was tested under the initial conditions $x(t) = [2 \ 0]^T$, $t \in [-0.4 \ 0]$ and uncertainty $F(t) = \begin{bmatrix} \sin(t) & 0 \\ 0 & \cos(t) \end{bmatrix}$.

Fig. 2. Control results for system (41) with uncertainties and with time varying-delay $\tau(t) = 0.25 + 0.15\sin(t)$

From the simulation results in figure 2, it can be clearly seen that our method offers a new approach to stabilize nonlinear systems represented by uncertain T-S fuzzy model with time-varying delay.

The second example illustrates the validity of the design method in the case of slow time varying delay ($\beta < 1$)

4.2 Example 2: Application to control a truck-trailer

In this example, we consider a continuous-time truck-trailer system, as shown in Fig. 3.

We will use the delayed model given by (Chen & Liu, 2005a). It is assumed that $\tau(t) = 1.10 + 0.75\sin(t)$. Obviously, we have $\bar{\tau} = 1.85$, $\beta = 0.75$. The time-varying delay model with uncertainties is given by

$$\dot{x}(t) = \sum_{i=1}^2 h_i(x_1(t)) [(A_i + \Delta A_i)x(t) + (A_{\tau i} + \Delta A_{\tau i})x(t - \tau(t)) + (B_i + \Delta B_i)u(t)] \quad (43)$$

where

$$A_1 = \begin{bmatrix} -a \frac{\bar{v}t}{Lt_0} & 0 & 0 \\ a \frac{\bar{v}t}{Lt_0} & 0 & 0 \\ a \frac{\bar{v}^2 t^2}{2Lt_0} & \frac{\bar{v}t}{t_0} & 0 \end{bmatrix}, A_{\tau 1} = \begin{bmatrix} -(1-a) \frac{\bar{v}t}{Lt_0} & 0 & 0 \\ (1-a) \frac{\bar{v}t}{Lt_0} & 0 & 0 \\ (1-a) \frac{\bar{v}^2 t^2}{2Lt_0} & 0 & 0 \end{bmatrix}$$

$$A_2 = \begin{bmatrix} -a \frac{\bar{v}t}{Lt_0} & 0 & 0 \\ a \frac{\bar{v}t}{Lt_0} & 0 & 0 \\ a \frac{dv^2 t^2}{2Lt_0} & \frac{dv\bar{t}}{t_0} & 0 \end{bmatrix}, A_{\tau 2} = \begin{bmatrix} -(1-a) \frac{\bar{v}t}{Lt_0} & 0 & 0 \\ (1-a) \frac{\bar{v}t}{Lt_0} & 0 & 0 \\ (1-a) \frac{dv^2 t^2}{2Lt_0} & 0 & 0 \end{bmatrix}$$

Fig. 3. Truck-trailer system

$$B_1 = B_2 = \left[\frac{v\bar{t}}{lt_0} \ 0 \ 0 \right]^T$$

$$\Delta A_1 = \Delta A_2 = \Delta A_{\tau 1} = \Delta A_{\tau 2} = MF(t)E$$

with

$$M = [0.255 \ 0.255 \ 0.255]^T, \ E = [0.1 \ 0 \ 0]$$

$$\Delta B_1 = \Delta B_2 = M_b F(t) E_b$$

with

$$M_b = [0.1790 \ 0 \ 0]^T, \ E_{b1} = 0.05, \ E_{b2} = 0.15$$

where

$$l = 2.8, L = 5.5, v = -1, \bar{t} = 2, t_0 = 0.5, a = 0.7, d = \frac{10t_0}{\pi}$$

The membership functions are defined as

$$h_1(\theta(t)) = \left(1 - \frac{1}{1 + \exp(-3(\theta(t) - 0.5\pi))}\right) \times \left(\frac{1}{1 + \exp(-3(\theta(t) + 0.5\pi))}\right)$$

$$h_2(\theta(t)) = 1 - h_1$$

where

$$\theta(t) = x_2(t) + a(v\bar{t}/2L)x_1(t) + (1 - a)(v\bar{t}/2L)x_1(t - \tau(t))$$

By using theorem 3, with the choice of $\lambda = 5$, we can obtain the following feasible solution:

$$P = \begin{bmatrix} 0.2249 & 0.0566 & -0.0259 \\ 0.0566 & 0.0382 & 0.0775 \\ -0.0259 & 0.0775 & 2.7440 \end{bmatrix}, \ S = \begin{bmatrix} 0.2408 & -0.0262 & -0.1137 \\ -0.0262 & 0.0236 & 0.0847 \\ -0.1137 & 0.0847 & 0.3496 \end{bmatrix}$$

$$Z = \begin{bmatrix} 0.0373 & 0.0133 & -0.0052 \\ 0.0133 & 0.0083 & 0.0202 \\ -0.0052 & 0.0202 & 1.0256 \end{bmatrix}, T = \begin{bmatrix} 0.0134 & 0.0053 & 0.0256 \\ 0.0075 & 0.0038 & -0.0171 \\ 0.0001 & 0.0014 & 0.0642 \end{bmatrix}$$
$$Y = \begin{bmatrix} -0.0073 & -0.0022 & 0.0192 \\ -0.0051 & -0.0031 & 0.0096 \\ 0.0012 & -0.0012 & -0.0804 \end{bmatrix}$$
$$\epsilon_{A1} = 0.1087, \epsilon_{A2} = 0.0729, \epsilon_{A12} = 0.1184$$
$$\epsilon_{A\tau1} = 0.0443, \epsilon_{A\tau2} = 0.0369, \epsilon_{A\tau12} = 0.0432$$
$$\epsilon_{B1} = 0.3179, \epsilon_{B2} = 0.3383, \epsilon_{B12} = 0.3250$$
$$K_1 = [3.7863 \ -5.7141 \ 0.1028]$$
$$K_2 = [3.8049 \ -5.8490 \ 0.0965]$$

The simulation was carried out for an initial condition $x(t) = [-0.5\pi \ 0.75\pi \ -5]^T, t \in [-1.85 \ 0]$.

Fig. 4. Control results for the truck-trailer system (41)

The third example is presented to illustrate the effectiveness of the proposed main result for fast time-varying delay system.

4.3 Example 3: Application to an inverted pendulum

Consider the well-studied example of balancing an inverted pendulum on a cart (Cao et al., 2000).

$$\dot{x}_1 = x_2$$

(44)

$$\dot{x}_2 = \frac{g \sin(x_1) - amlx_2^2 \sin(2x_1)/2 - a \cos(x_1)u}{4l/3 - aml \cos^2(x_1)}$$

(45)

Fig. 5. Inverted pendulum

where x_1 is the pendulum angle (represented by θ in Fig. 5), and x_2 is the angular velocity ($\dot{\theta}$). $g = 9.8m/s^2$ is the gravity constant, m is the mass of the pendulum, M is the mass of the cart, $2l$ is the length of the pendulum and u is the force applied to the cart. $a = 1/(m + M)$. The nonlinear system can be described by a fuzzy model with two IF-THEN rules:

Plant Rule 1: IF x_1 is about 0, Then

$$\dot{x}(t) = A_1 x(t) + B_1 u(t) \quad (46)$$

Plant rule 2: IF x_1 is about $\pm \frac{\pi}{2}$, Then

$$\dot{x}(t) = A_2 x(t) + B_2 u(t) \quad (47)$$

where

$$A_1 = \begin{bmatrix} 0 & 1 \\ 17.2941 & 0 \end{bmatrix}, A_2 = \begin{bmatrix} 0 & 1 \\ 12.6305 & 0 \end{bmatrix}$$

$$B_1 = \begin{bmatrix} 0 \\ -0.1765 \end{bmatrix}, B_2 = \begin{bmatrix} 0 \\ -0.0779 \end{bmatrix}$$

The membership functions are

$$h_1 = \left(1 - \frac{1}{1 + \exp(-7(x_1 - \pi/4))}\right) \times \left(1 + \frac{1}{1 + \exp(-7(x_1 + \pi/4))}\right)$$

$$h_2 = 1 - h_1$$

In order to illustrate the use of theorem (3), we assume that the delay terms are perturbed along values of the scalar $s \in [0, 1]$, and the fuzzy time-delay model considered here is as follows:

$$\dot{x}(t) = \sum_{i=1}^r h_i [((1-s)A_i + \Delta A_i)x(t) + (sA_{\tau i} + \Delta A_{\tau i})x(t - \tau(t)) + B_i u(t)] \quad (48)$$

where

$$A_1 = \begin{bmatrix} 0 & 1 \\ 17.2941 & 0 \end{bmatrix}, A_2 = \begin{bmatrix} 0 & 1 \\ 12.6305 & 0 \end{bmatrix}$$

$$B_1 = \begin{bmatrix} 0 \\ -0.1765 \end{bmatrix}, B_2 = \begin{bmatrix} 0 \\ -0.0779 \end{bmatrix}$$

$$\Delta A_1 = \Delta A_2 = \Delta A_{\tau 1} = \Delta A_{\tau 2} = MF(t)E$$

with

$$M = \begin{bmatrix} 0.1 & 0 \\ 0 & 0.1 \end{bmatrix}^T, E = \begin{bmatrix} 0 & 0 \\ 0 & 0.1 \end{bmatrix}$$

Let $s = 0.1$ and uncertainty $F(t) = \begin{bmatrix} \sin(t) & 0 \\ 0 & \cos(t) \end{bmatrix}$. We consider a fast time-varying delay $\tau(t) = 0.2 + 1.2 |\sin(t)|$ ($\beta = 1.2 > 1$).

Using LMI-TOOLBOX, there is a set of feasible solutions to LMIs (29).

$$K_1 = [159.7095 \ 30.0354], K_2 = [347.2744 \ 78.5552]$$

Fig. 4 shows the control results for the system (48) with time-varying delay $\tau(t) = 0.2 + 1.2 |\sin(t)|$ under the initial condition $x(t) = [2 \ 0]^T, t \in [-1.40 \ 0]$.

Fig. 6. Control results for the system (48) with time-varying delay $\tau(t) = 0.2 + 1.2 |\sin(t)|$.

5. Conclusion

In this chapter, we have investigated the delay-dependent design of state feedback stabilizing fuzzy controllers for uncertain T-S fuzzy systems with time varying delay. Our method is an important contribution as it establishes a new way that can reduce the conservatism and the computational efforts in the same time. The delay-dependent stabilization conditions obtained in this chapter are presented in terms of LMIs involving a single tuning parameter. Finally, three examples are used to illustrate numerically that our results are less conservative than the existing ones.

6. References

Boukas, E. & ElHajjaji, A. (2006). On stabilizability of stochastic fuzzy systems, *American Control Conference, 2006*, Minneapolis, Minnesota, USA, pp. 4362–4366.

- Cao, S. G., Rees, N. W. & Feng, G. (2000). h_∞ control of uncertain fuzzy continuous-time systems, *Fuzzy Sets and Systems* Vol. 115(No. 2): 171–190.
- Cao, Y.-Y. & Frank, P. M. (2000). Analysis and synthesis of nonlinear timedelay systems via fuzzy control approach, *IEEE Transactions on Fuzzy Systems* Vol. 8(No. 12): 200–211.
- Chadli, M. & ElHajjaji, A. (2006). A observer-based robust fuzzy control of nonlinear systems with parametric uncertainty, *Fuzzy Sets and Systems* Vol. 157(No. 9): 1279–1281.
- Chen, B., Lin, C., Liu, X. & Tong, S. (2008). Guaranteed cost control of t-s fuzzy systems with input delay, *International Journal Robust Nonlinear Control* Vol. 18: 1230–1256.
- Chen, B. & Liu, X. (2005a). Delay-dependent robust h_∞ control for t-s fuzzy systems with time delay, *IEEE Transactions on Fuzzy Systems* Vol. 13(No. 4): 544 – 556.
- Chen, B. & Liu, X. (2005b). Fuzzy guaranteed cost control for nonlinear systems with time-varying delay, *Fuzzy sets and systems* Vol. 13(No. 2): 238 – 249.
- Chen, B., Liu, X., Tang, S. & Lin, C. (2008). Observer-based stabilization of t-s fuzzy systems with input delay, *IEEE Transactions on fuzzy systems* Vol. 16(No. 3): 625–633.
- Chen, B., Liu, X. & Tong, S. (2007). New delay-dependent stabilization conditions of t-s fuzzy systems with constant delay, *Fuzzy sets and systems* Vol. 158(No. 20): 2209 – 2242.
- Guan, X.-P. & Chen, C.-L. (2004). Delay-dependent guaranteed cost control for t-s fuzzy systems with time delays, *IEEE Transactions on Fuzzy Systems* Vol. 12(No. 2): 236–249.
- Guerra, T., Kruszewski, A., Vermeiren, L. & Tirmant, H. (2006). Conditions of output stabilization for nonlinear models in the takagi-sugeno's form, *Fuzzy Sets and Systems* Vol. 157(No. 9): 1248–1259.
- He, Y., Wang, Q., Xie, L. H. & Lin, C. (2007). Further improvement of free-weighting matrices technique for systems with time-varying delay, *IEEE Trans. Autom. Control* Vol. 52(No. 2): 293–299.
- He, Y., Wu, M., She, J. H. & Liu, G. P. (2004). Parameter-dependent lyapunov functional for stability of time-delay systems with polytopic type uncertainties, *IEEE Trans. Autom. Control* Vol. 49(No. 5): 828–832.
- Kim, E. & Lee, H. (2000). New approaches to relaxed quadratic stability condition of fuzzy control systems, *IEEE Transactions on Fuzzy Systems* Vol. 8(No. 5): 523–534.
- Li, C., Wang, H. & Liao, X. (2004). Delay-dependent robust stability of uncertain fuzzy systems with time-varying delays, *Control Theory and Applications, IEE Proceedings, IET*, pp. 417–421.
- Lin, C., Wang, Q. & Lee, T. (2006). Delay-dependent lmi conditions for stability and stabilization of t-s fuzzy systems with bounded time-delay, *Fuzzy sets and systems* Vol. 157(No. 9): 1229 – 1247.
- Moon, Y. S., Park, P., Kwon, W. H. & Lee, Y. S. (2001). Delay-dependent robust stabilization of uncertain state-delayed systems, *International Journal of control* Vol. 74(No. 14): 1447–1455.
- Oudghiri, M., Chadli, M. & ElHajjaji, A. (2007). One-step procedure for robust output fuzzy control, *CD-ROM of the 15th Mediterranean Conference on Control and Automation, IEEE-Med'07, Athens, Greece*, pp. 1 – 6.
- Park, P., Lee, S. S. & Choi, D. J. (2003). A state-feedback stabilization for nonlinear time-delay systems: A new fuzzy weighting-dependent lyapunov-krasovskii functional approach, *Proceedings of the 42nd IEEE Conference on Decision and Control, Maui, Hawaii*, pp. 5233–5238.

- Wang, H. O., Tanaka, K. & Griffin, M. F. (1996). An approach to fuzzy control of nonlinear systems: Stability and design issues, *IEEE Transactions on fuzzy systems* Vol. 4(No. 1): 14–23.
- Wang, Y., Xie, L. & Souza, C. D. (1992). Robust control of a class of uncertain nonlinear systems, *Systems control letters* Vol. 19(No. 2): 139 – 149.
- Wu, H.-N. & Li, H.-X. (2007). New approach to delay-dependent stability analysis and stabilization for continuous-time fuzzy systems with time-varying delay, *IEEE Transactions on Fuzzy Systems* Vol. 15(No. 3): 482–493.
- Wu, M., He, Y. & She, J. (2004). New delay-dependent stability criteria and stabilizing method for neutral systems, *IEEE transactions on automatic control* Vol. 49(No. 12): 2266–2271.
- Xie, L. & DeSouza, C. (1992). Robust h_∞ control for linear systems with norm-bounded time-varying uncertainty, *IEEE Trans. Automatic Control* Vol. 37(No. 1): 1188 – 1191.
- Zhang, Y. & Heng, P. (2002). Stability of fuzzy control systems with bounded uncertain delays, *IEEE Transactions on Fuzzy Systems* Vol. 10(No. 1): 92–97.

IntechOpen

Recent Advances in Robust Control - Novel Approaches and Design Methods

Edited by Dr. Andreas Mueller

ISBN 978-953-307-339-2

Hard cover, 462 pages

Publisher InTech

Published online 07, November, 2011

Published in print edition November, 2011

Robust control has been a topic of active research in the last three decades culminating in H_2/H_∞ and μ design methods followed by research on parametric robustness, initially motivated by Kharitonov's theorem, the extension to non-linear time delay systems, and other more recent methods. The two volumes of Recent Advances in Robust Control give a selective overview of recent theoretical developments and present selected application examples. The volumes comprise 39 contributions covering various theoretical aspects as well as different application areas. The first volume covers selected problems in the theory of robust control and its application to robotic and electromechanical systems. The second volume is dedicated to special topics in robust control and problem specific solutions. Recent Advances in Robust Control will be a valuable reference for those interested in the recent theoretical advances and for researchers working in the broad field of robotics and mechatronics.

How to reference

In order to correctly reference this scholarly work, feel free to copy and paste the following:

Hamdi Gassara, Ahmed El Hajjaji and Mohamed Chaabane (2011). Robust Control of Nonlinear Time-Delay Systems via Takagi-Sugeno Fuzzy Models, Recent Advances in Robust Control - Novel Approaches and Design Methods, Dr. Andreas Mueller (Ed.), ISBN: 978-953-307-339-2, InTech, Available from: <http://www.intechopen.com/books/recent-advances-in-robust-control-novel-approaches-and-design-methods/robust-control-of-nonlinear-time-delay-systems-via-takagi-sugeno-fuzzy-models>

INTECH
open science | open minds

InTech Europe

University Campus STeP Ri
Slavka Krautzeka 83/A
51000 Rijeka, Croatia
Phone: +385 (51) 770 447
Fax: +385 (51) 686 166
www.intechopen.com

InTech China

Unit 405, Office Block, Hotel Equatorial Shanghai
No.65, Yan An Road (West), Shanghai, 200040, China
中国上海市延安西路65号上海国际贵都大饭店办公楼405单元
Phone: +86-21-62489820
Fax: +86-21-62489821

© 2011 The Author(s). Licensee IntechOpen. This is an open access article distributed under the terms of the [Creative Commons Attribution 3.0 License](https://creativecommons.org/licenses/by/3.0/), which permits unrestricted use, distribution, and reproduction in any medium, provided the original work is properly cited.

IntechOpen

IntechOpen