We are IntechOpen, the world's leading publisher of Open Access books Built by scientists, for scientists

6,300

Open access books available

172,000

International authors and editors

190M

Downloads

Our authors are among the

154

Countries delivered to

TOP 1%

most cited scientists

12.2%

Contributors from top 500 universities

WEB OF SCIENCE™

Selection of our books indexed in the Book Citation Index
in Web of Science™ Core Collection (BKCI)

Interested in publishing with us?
Contact book.department@intechopen.com

Numbers displayed above are based on latest data collected.
For more information visit www.intechopen.com

Bistable Photoconduction in Semiconductors

Stefano Lagomarsino

*Department of Physics - University of Florence
Italy*

1. Introduction

Bistable conduction in semiconductors, supported or not by an external source of ionizing radiation, has long been related to instabilities emerging in ionization-recombination processes. Under certain circumstances, a same applied voltage or a same irradiation level can produce two different current intensities, depending on the history of the biasing-irradiation settings, due to different conditions of equilibrium between the population levels of the impurity centers. The populations of the conduction and the valence band, along with those of the impurity inter-bandgap levels, depend in a complex way on the equilibrium between ionization, produced by irradiation and/or impact ionization by hot carriers, and recombination, mainly in deep impurity recombination centers. Since late fifties, negative conductivity regimes in doped semiconductors, exposed or not to ionizing irradiation, has revealed that more than one equilibrium point between ionization and recombination processes can hold in certain doping conditions, as evidenced by the typical S-shape of the current-voltage characteristics of the conductor (Khosla et al., 1973; Koenig, 1958). Several mechanisms has been invoked to explain the bistable behavior of semiconductors, all involving some kind of avalanche-related phenomenon: screening of the impurity charge by free carriers (Crandal, 1970; Kim & Yung, 2004; Stobbe et al., 1994; Yoffa, 1981) and excitation followed by ionization of metastable states of dopants (Brandl & Prettl, 1991; Schöll, 1982), are probably the most fortunate among them, but absolutely not the unique ones; dissipation effects (Golik et al., 1990; Koeppe & Urbelis, 1968), hole-assisted autocatalysis of electrons (Schöll, 1979), autocatalytic generation of excitons (Landsberg & Pimpale, 1976) have served as well to the modelling of some kind of negative conductivity regime. Moreover, other works report on possible instability mechanisms due to field dependent effects other than autocatalytic charge generation, namely field-enhanced trapping (Bonch-Bruevich et al., 1975) and Poole-Frenkel emission (Frenkel, 1938; Reggiani & Mitin, 1989). All these *ways* toward bistability suffer a common drawback from being all originated by electric-field related phenomena: thermodynamic considerations (Aoki, 2001; Schöll, 1987) prescribe that once the bistable regime has been reached, spatial patternization of high charge-density regions occurs spontaneously, manifesting itself in drops (Bel'kov et al., 1999) or much more often in filaments (Hirschinger et al., 2000). As a matter of fact, even though, at the beginning of these studies, application of bistable conduction was foreseen in switching devices and information storage (see e.g. the "cryosar" (Mcwhorter & Rediker, 1959; Menoret, 1968)), uncontrollable spatial patterns lead to the emergence of deterministic chaos, resulting in unreliable switching (K.Aoki & K.Yamamoto, 1989).

In this chapter, I report on a theoretical research about if and how a recombination bistability can occur supported *only* by light irradiance, in presence of arbitrarily small, or also null, electric field, in a way that this kind of bistability can be reliably employed in optoelectronic devices (Lagomarsino, 2007; 2008). In section 2 a very general result about stability of dynamical systems is stated, in order to determine conditions for photoconductive bistability. In section 3 some well known models of recombination bistability are resumed and studied with the aid of the stability criterion stated in section 2. The same criterion, in section 4, is employed to determine the two mechanisms which can assure bistability driven by light irradiance alone, with zero applied electric field. In section 5 and 6 these two mechanisms are studied in detail, and sufficient algebraic conditions on the recombination coefficients are found assuring photoconductive bistability in suitably doped semiconductors. Finally, in section 7 data from current literature are employed to study one of the centers which are the best candidates to exhibit a bistable recombination behavior driven by light irradiance in germanium.

2. A necessary condition for dynamical instability

The occurrence of multistability in a dynamical system implies its phase-space to be partitioned in domains which are mutually inaccessible, called basins of attraction. If two representative points, at a given instant of time, are arbitrarily close to each other, but belong to different, contiguous basins of attraction, the evolution of the two points will carry them, after a sufficient amount of time, sensitively apart from each other. Let a homogeneous system, subject to ionization-recombination processes, be adequately described by the populations of the atomic levels, in a way that the representative points of its phase space are given by the values of the populations themselves $N_1, N_2, \dots, N_k, \dots \equiv \{N_i\}$. If $\{N_i(t)\}$ is a trajectory of the system in the phase space, and $\{\delta N_i(t)\}$ is a perturbation, the existence of two or more basins of attraction can be excluded stating that, for each $\{N_i(0)\}$, a positive number ϵ exists such that, if $|\{\delta N_i(0)\}| < \epsilon$ then $\lim_{t \rightarrow \infty} |\{\delta N_i(t)\}| = 0$ (asymptotic stability). Now, let the rate equations of the system be the following:

$$\dot{N}_i = f_i(\{N_k\}). \quad (1)$$

The perturbation evolves in time according to the equations

$$\delta \dot{N}_i = \sum_j T_{ij} \delta N_j + o(\{\delta N_k\}) \text{ with } T_{ij} = \frac{\partial f_i}{\partial N_j}. \quad (2)$$

It is worth noting that from the neutrality condition $\sum_i N_i(t) = \text{const.}$ two statements about the matrix T_{ij} and the perturbation δN_i follow straightforwardly, namely

$$\sum_i T_{ij} = \frac{\partial}{\partial N_j} \frac{d}{dt} \sum_i N_i = 0, \quad (3)$$

and

$$\sum_i \delta N_i = 0. \quad (4)$$

Under these last assumptions, we will state some sufficient conditions on the Jacobian matrix T_{ij} under which any perturbation $\{\delta N_i(t)\}$ vanishes for time approaching infinity. Preliminarily, we assume that no rearrangement of the indexes exists such that $T_{ij} = 0$ for

all the $i \leq k$ and $j > k$, for a convenient k (irreducibility for permutations). In this way we exclude that the system can be divided into two or more non-interacting parts. In this case, the following, equivalent statements hold

- Non-negativity of the off-diagonal entries of T_{ij} , implies stability of the system.
- Dynamical instability requires as a necessary condition the negative sign of some off-diagonal entry of T_{ij} .

A first step to realize the truth of the two propositions derives from consideration of the matrix T_{ij} under the light of the first Gershgorin theorem (Todd, 1962), concerning the limitation of the eigenvalues of a (generally complex) matrix T_{ij} . The theorem affirms that every eigenvalue of the matrix belongs to some of the disks in the complex plane having centers in T_{jj} and radii $r_j \equiv \sum_{i \neq j} |T_{ij}|$. Due to the eq.3 and to the non-negativity of the off-diagonal entries, it follows that each T_{jj} is surely non-positive, and that $r_j = -T_{jj}$. Consequently (see also fig.1), all of the eigenvalues of the matrix have a real part either negative or null.

Fig. 1. Scheme of a 3×3 Jacobian matrix T with its eigenvalues and the relative Gershgorin disks in the complex plane.

Now, it is well known that the negative real part of *all* the characteristic exponents of the system could be a sufficient condition for dynamic stability (Minorsky, 1962). Nevertheless, eq. 3 implies singularity of the matrix T_{ij} , then at least one of the roots of the characteristic equation is null, and an asymptotic divergence of the rate equations cannot be excluded at this point, due to the higher order terms in eq.2. The key for the solution is to notice that the space S spanned by the points $\{\delta N_i\}$ satisfying condition 4 is closed with respect to the matrix T_{ij} , as can easily be seen by application of eq.3. Therefore, it will be sufficient to test the sign of the eigenvalues of T^S : the restriction to the space S of the linear operator defined by T_{ij} . To this aim, we recall two conclusions concerning sign-symmetric and irreducible matrices, reached by Hearon (Hearon, 1963) and more recently surveyed in the context of general M-matrix theory (see chapter 6 of Berman & Plemmons (1994)):

1. An eigenvector of the zero eigenvalue exists, such that all its components are positive.
2. The multiplicity of the zero characteristic exponent is one.

For statement 1, the eigenspace S_0 corresponding to the zero-eigenvector is not included in the space S spanned by the solutions of eq. 2, because its vectors do not satisfy condition 4.

Thus, S and S_0 both being closed with respect to the matrix T_{ij} , a similarity transformation A_{ij} exists such that

$$A^{-1}TA = \left(\begin{array}{c|c} 0 & 0 \\ \hline 0 & T^S \end{array} \right); \tag{5}$$

where T^S operates in the space S .
For statement 2, only one of the roots of the characteristic equation of T_{ij} vanishes, so that the eigenvalues of T^S are all non-zero, and equal the non-null eigenvalues of T_{ij} , which have negative real part. Since T^S is the restriction of T_{ij} to the space spanned by the solutions of system 2, the negative real part of its eigenvalues implies asymptotic stability. Of course, the negativity of some off-diagonal entry of the Jacobian matrix is not a sufficient, but only a necessary condition for instability; nevertheless it provides a very simple tool to greatly restrict the field of investigation and to identify all the relevant phenomena inducing bistability in ionization-recombination processes.

3. Avalance-related bistabilities in photoconductors

In this section we consider two well known cases of bistable photo-conduction triggered by impact ionization of impurities. Even if our principal aim in this chapter is the study of field-independent bistabilities, the study of two simpler cases provides useful illustrations of the necessary criterion for instability introduced in the previous section. Moreover, it will be useful as an introduction to some basic concepts largely employed in the following.

3.1 Screenig effect in impact ionization of one-level impurities

Let us consider a deep donor doped, partially compensated semiconductor, exposed to a sub-bandgap radiation which is able to ionize the donor centers (extrinsic photoconduction), and subject to an electric field strong enough to sustain impact ionization of impurities. Assuming n and n_t to be the concentration of the electrons in the conduction band and in the impurity centers, and being N_D and N_A the concentration of donor and acceptor centers, respectively, the rate equations of the system are the following (see also fig 2 (left) for a schematics of the transition rates):

$$\begin{aligned} \dot{n} &= (A_I n + A_R) n_t - B_T n (N_D - n_t) \quad \text{and} \quad \dot{n}_t = -\dot{n} \\ \text{with} \quad n + n_t &= N_D - N_A. \end{aligned} \tag{6}$$

In eq.6, A_R is a generation term proportional to the radiation irradiance, B_T is a recombination

Fig. 2. Diagram of the transitions for a one-level and a two-levels impurity.

coefficient, and A_I is the impact ionization coefficient, depending on the electric field and on

the shielding of charged scatterers produced by the free electrons themselves, and given by Aoki (2001):

$$A_I = A_I^0(E) + \sigma n. \quad (7)$$

At equilibrium, when $\dot{n} = \dot{n}_t = 0$, equation 6 reduces, in the adimensional variable $x = \frac{n}{N_D - N_A}$, to:

$$x^3 - \alpha x^2 + \beta x - \gamma = 0, \quad (8)$$

with the coefficients α , β and γ given by:

$$\alpha = 1 - \frac{A_I^0 + B_T}{\sigma(N_D - N_A)}, \quad \beta = \frac{A_R}{\sigma(N_D - N_A)^2} - \frac{A_I^0 - B_T \frac{N_A}{N_D - N_A}}{\sigma(N_D - N_A)}, \quad \gamma = \frac{A_R}{\sigma(N_D - N_A)^2}. \quad (9)$$

In order to occur bistability, equation 8 has to admit three real and positive solutions, which is true if and only if the following inequalities hold:

$$\left(\alpha^3 - \frac{9}{2}\alpha\beta + \frac{27}{2}\gamma\right)^2 < (\alpha^2 - 3\beta)^3, \quad \text{for reality,} \\ \alpha > 0, \quad \beta > 0, \quad \gamma > 0, \quad \text{for positivity.} \quad (10)$$

The points (α, β, γ) satisfying the inequalities 10, identify a region Ω in the three-dimensional space which is represented in figure 2, along with two sections ω_γ and ω_α parallel to the $\alpha\beta$ and to the $\beta\gamma$ plains, respectively. The geometric locus χ of the cusp points C_γ (or C_α) is given by the curve whose equations are $\beta = \frac{1}{3}\alpha^2$ and $\gamma = \frac{1}{27}\alpha^3$.

In order for the system to undergo bistable transitions, the curve described in the $\alpha\beta\gamma$ space by the representative point of the system, while varying the radiation irradiance term A_R , has to cross through the bistability region Ω . Since in this case the curve is simply a straight line r parallel to the $\beta\gamma$ plane and starting, for $A_R = 0$, from a point P_0 on the $\alpha\beta$ plain, it is sufficient to impose that P_0 doesn't belong to the region Ω and the cusp point $C_{\alpha_0} = \left(\frac{1}{3}\alpha_0^2, \frac{1}{27}\alpha_0^3\right)$ lays under the straight line r in the plane $\beta\gamma$ (see also fig.3b (left)). Simple though annoying algebra shows that these two conditions hold if the ionization and recombination coefficients satisfy the following inequalities:

$$\left(\frac{A_I^0 + B_T}{\sigma(N_D - N_A)}\right)^2 + \frac{2A_I^0}{\sigma(N_D - N_A)} - \frac{N_D + N_A}{N_D - N_A} \frac{2B_T}{\sigma(N_D - N_A)} + 1 < 0, \\ \left(1 - \frac{A_I^0 + B_T}{\sigma(N_D - N_A)}\right)^2 \left(8 + \frac{A_I^0 + B_T}{\sigma(N_D - N_A)}\right) > 27 \frac{B_T \frac{N_A}{N_D - N_A} - A_I^0}{\sigma(N_D - N_A)}. \quad (11)$$

In figure 4 the area in the $A_I^0 B_T$ plane satisfying rel.11 is shown for several values of the ratio N_D/N_A . It is quite evident, from inspection of the figure, that once known the screening and the recombination coefficients, the bandgap can be tailored, by suitable choice of N_D and N_A , in order to manifest photoconductive bistability.

Let us consider, now, the Jacobian matrix T_{nn_t} of the system 6:

$$T = \begin{pmatrix} n_t \frac{\partial}{\partial n} (A_I n) - B_T (N_D - n_t) & A_I n + A_R + B_T n \\ -n_t \frac{\partial}{\partial n} (A_I n) + B_T (N_D - n_t) & -A_I n - A_R - B_T n \end{pmatrix}; \quad (12)$$

Fig. 3. (a) Diagram of the Ω region in the $\alpha\beta\gamma$ space, whose points correspond to three states of equilibrium, two stable and one unstable; χ is the geometric locus of the cusp points. (b-left) Section of the Ω region in a plane with $\alpha = \text{const.}$ (b-right) Section of the Ω region in a plane with $\gamma = \text{const.}$

according to the stability criterion of the non-negativity of the off-diagonal terms, stated in the preceding section, the observation of the Jacobian matrix simply gives the indication that, in order for the bistability to occur, the impact ionization term A_I has to be nonnull. Compared with eq. 11 this seems a quite poor and qualitative information, but we will verify how, in more complex situations, with an arbitrary number of energy levels, for instance, this kind of insight will be of unvaluable usefulness.

3.2 impact excitation and ionization of metastable states

A widely adopted model of impact ionization introduced by Schöll (1987), suggests that the impact ionization processes of impurity multilevels can induce bistable conduction in semiconductors. Here we extend the model to the photo-ionization of the impurity levels and neglect thermal excitation and ionization of the deep donor centers. Given n , n_0 and n_1 the population of the conduction band, the ground and the excited level of the donor centers,

Fig. 4. In grey, the areas in the $A_I B_T$ plane which correspond to bistable situations, for different values of the constant N_D/N_A .

respectively, the rate equations of the system are:

$$\begin{aligned} \dot{n} &= (A_{I1}n + A_{R1})n_1 + (A_{I2}n + A_{R2})n_2 - B_Tn(N_D - n_1 - n_2), \\ \dot{n}_2 &= -(A_{I2}n + A_{R2})n_2 + B_Tn(N_D - n_1 - n_2) - Rn_2, \\ \dot{n}_1 &= -(A_{I1}n + A_{R1})n_1 + Rn_2, \\ \text{with } n + n_1 + n_2 &= N_D. \end{aligned} \tag{13}$$

Given $x = n/N_D$, and considering that the ratio of the generation terms $A_{R2}/A_{R1} \equiv \rho$ the solving equation at the equilibrium is again of the type of eq.8, with the coefficients α , β and γ equalling:

$$\begin{aligned} \alpha &= \frac{N_D A_{I1} A_{I2} - R(A_{I1} + B_T) - A_{R1}(\rho A_{I1} + A_{I2} + B_T)}{N_D A_{I1}(A_{I2} + B_T)}, \\ \beta &= \frac{\rho A_{R1}^2 + A_{R1}(R - \rho A_{I1} N_D - A_{I2} N_D) - A_{I1} R N_D}{N_D^2 A_{I1}(A_{I2} + B_T)}, \\ \gamma &= \frac{\rho A_{R1}^2 + A_{R1} R}{N_D^2 A_{I1}(A_{I2} + B_T)}. \end{aligned} \tag{14}$$

In this case, the curve describing the system in the $\alpha\beta\gamma$ space is of the second order in the generation term, and the algebraic discussion of its intersection with the region Ω is considerably more complex.

The stability criterion of the non-negativity of the off-diagonal entries of the Jacobian matrix of the system can give useful insight in the physics of the processes. These have the following values:

$$\begin{aligned} T_{nn_1} &= A_{I1}n + A_{R1} + B_Tn, \quad T_{nn_2} = A_{I2}n + A_{R2} + B_Tn, \\ T_{n_1n} &= -n_1 \frac{\partial}{\partial n} (A_{I1}n), \quad T_{n_1n_2} = R, \\ T_{n_2n} &= B_T(N_D - n_1 - n_2) - n_2 \frac{\partial}{\partial n} (A_{I2}n), \quad T_{n_2n_1} = -B_Tn, \end{aligned} \tag{15}$$

As expected, also for the Schöll model, the non-negativity of the off diagonal entries, along with the stability of the system, are not guaranteed if the impact ionization coefficients $A_{I1,2}$ are nonnull. Moreover, one of the non-diagonal terms is negative independently on the ionization mechanism, only due to the new recombination channel given by the metastable state, determining the term $-B_T n$ in eqs.15. This seems to open the way to some kind of different instability mechanism, independent on the electric field and determined only by the competition of different recombination channels. The next section will be devoted to the throughout investigation of all the possible mechanisms which can break the sign-symmetry of the Jacobian matrix of a system subject to ionization-recombination processes. The analysis will evidence the existence of two possible ways toward instability in photoconductors with zero electric field.

4. Dynamical instability in ionization-recombination reactions

If r_{ik} represents the number of electrons that, in the unit time, change their state from k to i , the functions f_i in eq.1 have the form

$$f_i = \sum_{k \neq i} (r_{ik} - r_{ki}) \quad (16)$$

The transition rates r_{ik} , in their turn, depend on the occupation numbers N_l in one of the following two ways:

$$\text{excitation-relaxation} \quad r_{ik} = R_{ik}(\{N_l\}) N_k^A \quad (17)$$

$$\text{ionization-recombination} \quad r_{ik} = S_{ik}(\{N_l\}) N_k^A N_i^F \quad (18)$$

where N_k^A is the number of electrons in the state k which are available to make a transition to another state, while N_i^F is the number of free places in the state i . Transition probabilities S_{ik} and R_{ik} may depend or not on the occupation numbers $\{N_l\}$, according to the nature of the reactions involved. For example, in impact ionization and in Auger recombination, S_{ik} depends on the number of free electrons. N_k^A and N_i^F , on the other hand, depend on the nature of the state labelled by the index. Figure 5 gives a schematics of the various cases involved in neutral and singly ionized atoms (left side of the figure), multiply ionized atoms (right side) and free states (top of the figure).

- *Neutral or singly ionized atoms.* Since all the valence electrons can be excited or extracted from the atoms, the number N_k^A of electrons available to make a transition is simply N_k . On the other hand, the number of "free places" for an electron to recombine is given by the number of ions, then

$$\begin{aligned} N_k^A &= N_k \\ N_i^F &= g_i - \sum_l \Delta_{il} N_l, \end{aligned} \quad (19)$$

where g_i is the number of atoms of the specie labelled by i , while Δ_{il} is equal to one only if i and l refer to states of a same atomic specie, otherwise is zero (notice that the index labels both the atomic specie and the energy level).

Fig. 5. A schematics of the transitions described by the model represented by eq. 17 and 18. On the left side, a set of atoms of a given specie is represented, each with its level diagram, three of whom are neutral and two singly ionized. On the right side, a set of neutral, singly or multiply ionized atoms are represented. In this case, the excited levels of each configuration are disregarded, in the assumption that their population is ruled by lattice or free charges temperature. The upper side represents the unbound state.

- *multiply ionized atoms.* Let the indexes k^- , k and k^+ indicate three adjacent energy levels in a given atomic configuration. An electron in the state k can make a transition in low energy processes only if no other electrons occupy the state k^+ in the same atom. Analogously, a free state k can be reached by an unbound electron only if the state k^- is occupied in its turn. Consequently, we have

$$\begin{aligned} N_k^A &= N_k - N_{k^+} \\ N_i^F &= N_{i^-} - N_i \end{aligned} \tag{20}$$

- *Free states.* If g_i is the degeneration of an unbound state, we can obviously state

$$\begin{aligned} N_k^A &= N_k \\ N_i^F &= g_i - N_i \end{aligned} \tag{21}$$

It is worth noting that, if we formally state $N_{k^+} = 0$ and $N_{i^-} = g_i$, the present case reduces to the previous one, which will be useful in the following discussion.

Once the expressions for the transition probabilities r_{ik} are determined by eq.17-18, the entries of the matrix T_{ij} are calculated from their derivatives with respect to the occupation numbers, as given in eq.2 , and can be then expressed as a sum of two contributions:

$$\begin{aligned} T_{ij} &= T_{ij}^{\text{nc}} + T_{ij}^{\text{c}} \quad \text{with} \\ T_{ij}^{\text{nc}} &= \sum_{k \neq i} \left(S_{ik} \frac{\partial N_k^A N_i^F}{\partial N_j} - S_{ki} \frac{\partial N_i^A N_k^F}{\partial N_j} \right) + \left(R_{ik} \frac{\partial N_k^A}{\partial N_j} - R_{ki} \frac{\partial N_i^A}{\partial N_j} \right) \text{ and} \\ T_{ij}^{\text{c}} &= \sum_{k \neq i} \left(\frac{\partial S_{ik}}{\partial N_j} N_k^A N_i^F - \frac{\partial S_{ki}}{\partial N_j} N_i^A N_k^F \right) + \left(\frac{\partial R_{ik}}{\partial N_j} N_k^A - \frac{\partial R_{ki}}{\partial N_j} N_i^A \right). \end{aligned} \tag{22}$$

The apices "nc" and "c" refer respectively to "non catalytic" and "catalytic" processes. In fact, T_{ij}^c is non-zero only if the transition probabilities S_{ik} and R_{ik} depend explicitly on $\{N_l\}$, that is, if the transition of an electron from state k to i is catalyzed or somewhat influenced by the presence of electrons in some specific quantum state. If this is not the case, only the T_{ij}^{nc} (non-catalytic) term is non zero. In this last case, the equations of the system 1 are of the second degree in $\{N_i\}$. Indeed, non linearity of the second order has been known to be a cause of instability in dynamical systems since the very beginning of chaos studies (Lorentz, 1963; Roessler, 1976). Nevertheless, almost without exceptions, only catalytic processes have been considered as possible mechanisms leading to instability in semiconductors. In the following we will study non-catalytic processes, the only ones which can hold in absence of an externally applied electric field.

- *Neutral or singly ionized atoms.* The rate equations assume the form (from eq.16,19,22)

$$\dot{N}_i = \sum_{l \neq i} \left\{ \left[S_{il} \left(g_i - \sum_k \Delta_{ik} N_k \right) + R_{il} \right] N_l \right\} - \left\{ \sum_{l \neq i} \left[S_{li} \left(g_l - \sum_k \Delta_{lk} N_k \right) + R_{li} \right] \right\} N_i \quad (23)$$

while the off-diagonal entries of the matrix T_{ij} are

$$T_{ij} = T_{ij}^{nc} = S_{ij} \left(g_i - \sum_l \Delta_{il} N_l \right) + S_{ji} N_i + R_{ij} - \Delta_{ij} S_{ij} N_j + \sum_{l \neq i,j} \left(\Delta_{lj} S_{ki} N_i - \Delta_{ij} S_{il} N_l \right) \quad (24)$$

Observing eq. 24, we notice that the only way for the off-diagonal entries to assume a negative value is to admit transitions involving several excited states of a same atomic specie, corresponding to the terms $-\Delta_{ij} S_{ik} N_k$ and $-\Delta_{ij} S_{ij} N_j$. These transitions may be free carrier capture or emission, or also electron exchange by tunneling between impurities in solid state plasmas. Even in these cases, however, the negative contributions of the expression can be overwhelmed if the exchange contributions are lesser than the collisional or radiative rates R_{ij} , which are always positive. In conclusion, instability, if any, requires electron exchange with metastable states and low excitation-relaxation rates.

- *Multiply ionized atoms* Sufficiently high collisional rates involve stability in case of single ionization, as just shown. This is not necessarily true for multiple ionization. If the collisional rates are high enough to thermalize the distribution of the excited levels of each electronic configuration, the transition probabilities S_{ij} between configurations depend on temperature, and the rate equations can be written in the following form (from eq.16,19,22):

$$\dot{N}_i = \sum_{k \neq i} [S_{ik} (N_{i-} - N_i) (N_k - N_{k+}) - S_{ki} (N_{k-} - N_k) (N_i - N_{i+})] \quad (25)$$

This equation describes not only electronic exchange between singly or multiply ionized atoms, but also ionization or recombination toward or from an unbound state k , formally stating $N_{k+} = 0$ and $N_{k-} = g_k$. For $i \neq j, j^\pm$, the off-diagonal terms of the Jacobian matrix T_{ij} assume the simple form:

$$T_{ij} = T_{ij}^{nc} = (S_{ji} - S_{j+i}) (N_i - N_{i+}) + (S_{ij} - S_{ij-}) (N_{i-} - N_i) \quad (26)$$

Since N_i and N_{i-} are always not less than N_{i+} and N_i , respectively, sufficient conditions for non-negativity of eq.26, and than for the stability of the dynamic system, are: $S_{ij} \geq S_{ij-}$ and

$S_{ji} \geq S_{j+i}$ for every i and j . That is, non-negativity of T_{ij} is assured if any further ionization of less ionized atoms is more favored than the more ionized ones, and recombination of the more ionized atoms is more probable compared with the less ionized. This is effectively true for shallow states of the band gap of semiconductors, but for deeper states the opposite can hold, due to the high energy transfer required by the recombination in deep centers, which make the multiphonon or radiative transition less likely than the phonon-cascade trapping by the shallower levels. Infact, several deep recombination centers in low-bandgap semiconductors manifested this behavior since the very beginning of the studies on limiting charge life-time centers (Wertheim, 1959). Particularly, in the last years an extensive thermal spectroscopy study revealed that this behavior is quite common for transition metals in semiconductors (Grillenberger, 2004; Knack et al., 2002; Sachse et al., 2000; Shiraishi et al., 1999; Yarykin et al., 1999).

In conclusion, we have shown that dynamical instability in ionization-recombination processes, in absence of electric fields sustaining catalytic carriers generation, requires the occurring of one of the following conditions:

- electronic exchange with metastable states with low excitation-relaxation rates;
- inversion of transition probability in multiply ionized atoms.

In the next sections, sufficient conditions on the recombination coefficients will be given for the occurring of bistability in each of the two cases.

5. Bistability by meta-stable states of recombination centers

We will study the equilibrium, under over-bandgap irradiation, of a semiconductor in which recombination is assured by deep donor centers (density M) admitting a metastable excited state. Since the general case would require discussion of a 5th-degree equation, we restrict to the case of a semiconductor strongly doped (density $N \gg M$) with shallow donor or acceptor impurities, that, as shall be seen, substantially reduces the algebraic complexity of the problem. The rate equations of the system (see fig. 5, left) for a schematics of the transition rates) are the following:

$$\begin{aligned}\dot{n} &= -(C_{1n} + C_{2n})n(M - n_1 - n_2) + g, \\ \dot{n}_2 &= C_{2n}n(M - n_1 - n_2) - C_{2p}pn_2 - R_{21}n_2, \\ \dot{n}_1 &= C_{1n}n(M - n_1 - n_2) - C_{1p}pn_2 + R_{21}n_2, \\ \dot{p} &= -(C_{1p}n_1 + C_{2p}n_2)p + g; \\ \text{with } n + n_1 + n_2 - M \pm N &= p.\end{aligned}\quad (27)$$

Let us express the constant and variable quantities of the system 27 in term of the adimensional parameters:

$$\begin{aligned}x &= \frac{p}{N}, y = \frac{n}{N}, y_i = \frac{n_i}{N}, \\ R_i &= \frac{C_{ip}}{C_{in}}, \rho = \frac{R_{21}}{N\sqrt{C_{1n}C_{2n}}}, K_i = \frac{C_{in}}{\sqrt{C_{1n}C_{2n}}}, G = \frac{g}{NM\sqrt{C_{1n}C_{2n}}}.\end{aligned}\quad (28)$$

Fig. 6. The levels diagram of a semiconductor doped with a deep level having; (left) a metastable excited state or (right) two different ionized states.

From the second and the third equation of system 27, we can calculate y_i :

$$\begin{aligned} y_1 &= \frac{R_2xy + (K_1 + K_2)\rho y}{R_1R_2x^2 + (R_1 + R_2)xy + (K_1 + K_2)\rho y + \rho K_1R_1x}, \\ y_2 &= \frac{R_1xy}{R_1R_2x^2 + (R_1 + R_2)xy + (K_1 + K_2)\rho y + \rho K_1R_1x}. \end{aligned} \quad (29)$$

Substituting eqs.29 in the first and the last equation of system 27, we obtain a system of two equations in the x and y unknowns:

$$\begin{aligned} \frac{(K_1 + K_2)(R_1R_2x^2y + \rho K_1R_1x)}{R_1R_2x^2 + (R_1 + R_2)xy + (K_1 + K_2)\rho y + \rho K_1R_1x} &= G, \\ y - x \mp 1 - \frac{M}{N} \frac{R_1R_2x^2 + \rho K_1R_1x}{R_1R_2x^2 + (R_1 + R_2)xy + (K_1 + K_2)\rho y + \rho K_1R_1x} &= 0. \end{aligned} \quad (30)$$

As announced, in the general case the solving equation of the system is of the fifth grade, but if $\frac{M}{N} \ll 1$ the second equation is linear, and the system reduces to a third degree equation of the type $x^3 - \alpha x^2 + \beta x - \gamma$ (equation 8), with

$$\begin{aligned} \alpha &= G \frac{R_1R_2 + R_1 + R_2}{(K_1 + K_2)R_1R_2} \mp 1, \\ \beta &= \left[1 - GK_1 \left(1 + \frac{(K_1 + K_2)K_1(\rho K_2 \pm 1) \pm (R_1 + R_2)}{\rho K_1R_1} \right) \right] \frac{1}{(K_1 + K_2)K_2R_1R_2}, \\ \gamma &= \pm G \frac{\rho}{R_1R_2}. \end{aligned} \quad (31)$$

From a first inspection of the third definition of system 31 and of the inequalities 10, p -doping results to be incompatible with bistability if recombination is assured by deep donors, because in this case γ would be negative. On the other hand, in case of n -doping, the representative points $(\alpha(G), \beta(G), \gamma(G))$ of the system in the $\alpha\beta\gamma$ space belong to a straight half-line starting from the $\alpha\beta$ plain and lying on the semi-space with $\gamma \geq 0$. In this case, bistability can hold if the straight line passes under the cusp line χ (see fig. 3b, left). This happens if the following necessary and sufficient condition holds:

$$\gamma(G_0) < \frac{1}{27}\alpha(G_0)^3 \quad \text{with} \quad \beta(G_0) = \frac{1}{3}\alpha(G_0)^2. \quad (32)$$

Fig. 7. (left) bistability by excited levels: lines which define the bistable region of the plane $R_1 R_2$ for different values of $\frac{K_2}{K_1}$ and for the value of ρ which make maximum the area of the bistable region itself. (right) bistability by multiply charged centers: lines which define the bistable region of the plane $R_1 R_2$ for different values of $\frac{K_2}{K_1}$.

It is found that the inequality 32 is satisfied if, for given values of $\frac{K_2}{K_1} = \sqrt{\frac{C_{2n}}{C_{1n}}}$ and $\rho = \frac{R_{21}}{N\sqrt{C_{1n}C_{2n}}}$, the points (R_1, R_2) , belong to the area below a given line. Since for a given recombination center the parameter ρ is inversely proportional to the doping density N , the bistable zone below the line can be made maximum by tuning the parameter ρ . In figure 7 (left), several lines are represented with $0.01 \leq \frac{K_2}{K_1} \leq 1000$, with the values of ρ corresponding to the maximum area. From their inspection, bistability results to be possible practically for all the values of R_1 , if R_2 is sufficiently small and/or $\frac{K_2}{K_1}$ is not too small or large respect to the unit. As a matter of fact, capture of an electron in the excited state by a positive center seems much more likely than capture of a hole by the neutral excited state, especially if the latter is closer to the conduction band than to the valence one, so that $R_2 = \frac{C_{2p}}{C_{2n}}$ is likely very small. In conclusion, bistable photoconduction in semiconductors, if recombination is assured by deep centers with metastable states, appears likely to be feasible by suitable choice of the doping parameters M and N and of the irradiation conditions.

6. Bistability by multiply ionized recombination centers

Photoconductive instability is possible, in case of multiply charged recombination centers, if the capture of a carrier by a neutral center is less likely than trapping by the center which have the same charge of the carrier itself, in spite of columbic repulsion (see section 4). This seemingly unlikely condition happens to be verified by several transition metal impurities in germanium, silicon, silicon carbide (Grillenberger, 2004; Knack et al., 2002; Sachse et al., 2000; Shiraishi et al., 1999; Wertheim, 1959; Yarykin et al., 1999), both in case of doubly and triply ionized centers. A treatment of photoconduction in semiconductor in which recombination is assured by multiply ionized centers can be found in ref.(Lagomarsino, 2008), where cases of double or triple donors or acceptors, donor-acceptors, double donor-acceptors, ecc. are studied in a general perspective. Here we restrict to the case of double acceptor impurities,

which happens to comprehend the more interesting practical case. The rate equations of the system, in this case, are the following (see also fig.5 right):

$$\begin{aligned}\dot{n} &= g - C_{2n}n(n_1 - n_2) - C_{1n}n(M - n_1), \\ \dot{n}_2 &= C_{2n}n(n_1 - n_2) - C_{2p}pn_2, \\ \dot{n}_1 &= C_{1n}n(M - n_1) - C_{1p}p(n_1 - n_2), \\ \dot{p} &= g - C_{2p}pn_2 - C_{1p}p(n_1 - n_2), \\ n + n_1 + n_2 - p - N &= 0\end{aligned}\quad (33)$$

We will consider all the parameters and the unknown quantities expressed in terms of the following, non-dimensional parameters:

$$\begin{aligned}x &= \frac{p}{n}, \quad y = \frac{n}{N}, \quad y_i = \frac{n_i}{M} \quad R_i = \frac{C_{ip}}{C_{in}}, \\ K_i &= \frac{C_{in}}{(C_{1n}C_{2n})^{1/2}}, \quad G = \frac{g}{NM(C_{1n}C_{2n})^{1/2}}.\end{aligned}\quad (34)$$

As a consequence, the second and the third of Eqs. 33 give, at equilibrium ($\dot{n}_i = 0$), the following conditions:

$$y_1 = \frac{1 + R_2x}{1 + R_2x + R_1R_2x^2}, \quad y_2 = \frac{1}{1 + R_2x + R_1R_2x^2}.\quad (35)$$

Their substitution in the first and the last of eqs.33 gives:

$$\begin{aligned}y &= G \frac{1 + R_2x + R_1R_2x^2}{K_2R_2x + K_1R_1R_2x^2}, \\ y &= \frac{1}{1 - x} \left(1 - \frac{M}{N} \frac{2 + R_2x}{1 + R_2x + R_1R_2x^2} \right).\end{aligned}\quad (36)$$

Although the solving equation of the system, in the general case, is of the fifth degree in the unknown x , if the concentration of deep centers is much lower than that of the dopants ($M \ll N$), the second of the Eqs.36 reduces to: $y = \frac{1}{1-x}$, and the solving equation reduces to one of the third degree of kind $x^3 - \alpha x^2 + \beta x - \gamma = 0$ (eq.8), with

$$\alpha = 1 - \frac{1}{R_1} - \frac{K_1}{G}, \quad \beta = \frac{1}{R_1} \left(\frac{K_2}{G} + \frac{1}{R_2} - 1 \right), \quad \gamma = \frac{1}{R_1R_2}.\quad (37)$$

In order to find conditions for bistability, one has to state which values of the parameters K_i and R_i make the coefficients α, β, γ to satisfy the inequalities 10 for some positive value of the control parameter G . Since G is not contained in γ , we can consider, for a given value of γ , the 2-dimensional set ω_γ of the couples (α, β) which satisfies the inequalities 10. The shape of ω_γ is shown in fig.3b (right), with a cusp point $C(\gamma)$ whose coordinates are

$$C(\gamma) = (\alpha_\gamma, \beta_\gamma) = \left(3\gamma^{\frac{1}{3}}, 3\gamma^{\frac{2}{3}} \right).\quad (38)$$

By elimination of G in the first two equations of 37, we find that the coefficients α and β define a straight line r with a negative angular coefficient in the plane $\alpha\beta$. This line crosses the region ω_γ if and only if the cusp point C_γ lies below it, that means

$$\beta_\gamma + \frac{K_2}{K_1 R_1} \alpha_\gamma < \frac{1}{R_1} \left[\frac{K_2}{K_1} \left(1 - \frac{1}{R_1} \right) + \frac{1}{R_2} - 1 \right]. \quad (39)$$

From this expression, taking into account expressions 38 and 37, it turns out that recombination bistability is possible if and only if the following inequality holds:

$$3 \left(\frac{K_1}{K_2} \left(\frac{R_1}{R_2^2} \right)^{\frac{1}{3}} + \left(\frac{1}{R_1 R_2} \right)^{\frac{1}{3}} \right) + \frac{K_1}{K_2} \left(1 - \frac{1}{R_2} \right) + \frac{1}{R_1} < 1 \quad (40)$$

This inequality gives a necessary and sufficient condition for having photoconductive multistability driven by the generation factor g . In the three-dimensional space-parameters given by R_1, R_2 and $\frac{K_2}{K_1}$, the region satisfying the inequality 40 is divided into two distinct branches. The first branch lies in the region with $\frac{K_2}{K_1} > 1$ and $R_1 > 1$, the second one in the "slice" $0 < R_2 < 1$. Nevertheless, only the first branch has a physical meaning, because the values of the parameters corresponding to the second branch give bistability only if $G < 0$. The projection of the first branch on the $R_1 R_2$ plane is shown in Fig.7 (right), for several values of $\frac{K_2}{K_1}$.

From the inspection of fig.7 we can set the rule of thumb according to which bistability occur if:

1. $\frac{K_2}{K_1}$ is large enough, and in any case greater than 1. That is, the charged center capture another carrier of the same charge more easily than the neutral one in spite of columbic repulsion.
2. R_1, R_2 are sufficiently large too, and R_1 is in any case greater than 1. That is, the columbic capture cross-section of the charged centers for the opposite-charged carriers is higher than that for the carriers of the same polarity (which is generally true);

condition 1 has been stated in section 4 as a necessary condition for dynamical instability referred to an arbitrary number of states of charge. Relation 40 also gives a sufficient condition for doubly charged centers.

It will be useful for the following considerations to infer the order of magnitude of the generation factor g and the time scale τ involved in the bistable transition. From Eqs. 38 and 37, we have, for the value G_γ at the cusp point $C(\gamma)$:

$$G_\gamma = K_1 \left(1 - \frac{1}{R_1} - \frac{3}{(R_1 R_2)^{\frac{1}{3}}} \right)^{-1}, \quad (41)$$

which gives, in the limit $R_{1,2} \gg 1$ (condition 2):

$$G_\gamma \approx K_1 \text{ thus } g_\gamma \approx NMC_{1n}. \quad (42)$$

The time scale τ can be obtained expressing Eq.33 in term of the adimensional parameters, which gives:

$$\tau \frac{dy}{dt} = G - \sum_{i=1}^2 K_i y (y_{i-1} - y_i), \quad \text{with } \tau = \frac{1}{M (C_{1n} C_{2n})^{1/2}}. \quad (43)$$

7. One example of possible photoconductive bistable behavior in germanium

In order to design a practical bistable photoconductive device, an accurate determination of the recombination center's trapping parameters is necessary in two respects: first, the values of the capture coefficients of a center having either multiple states of charge or excited metastable levels, define if the center is or not a candidate to exhibit multistability; second, the same values determine which are the more suitable values of the doping densities in order to obtain bistability for the desired radiation irradiances and with the appropriate response time.

Even though several deep centers having metastable electronic states are known, especially in large bandgap semiconductors (Ganichev et al., 1997; Ghosh et al., 1973; Jelezko & Wrachtrup, 2006; Pagonis et al., 2010), there is no plenty of detailed studies about the capture cross-section of both the ground and the excited state. For instance, for native EL2 centers in gallium arsenide, undoubtedly one of the most studied (Delaye & Sugg, 1994; Lin et al., 2006; Sudzius et al., 1999; Vincent et al., 1982), $R_1 = C_{1p}/C_{1n}$ (see section 5) is known to vary in the range $10^{-3} - 1$ from the ambient to cryogenic temperatures, the dependence of its recovery rate R_{21} (having an activation energy of about 0.3 eV) on temperature is also reported, but the capture rates of the metastable level are only known to be much smaller than those of the ground level (Delaye & Sugg, 1994), without any indication on the value of their ratio.

In comparison, the capture rates of multiply charged recombination centers have been studied in more detail, and several transition metal impurities in silicon, germanium and silicon carbide have exhibited a favourable ratio of the higher level cross section to the lower level one ($K_2/K_1 > 1$, see section 6) (Grillenberger, 2004; Knack et al., 2002; Sachse et al., 2000; Shiraishi et al., 1999; Wertheim, 1959; Yarykin et al., 1999). Here we present a study on a center which is likely the most deeply and the longest studied of these, namely Nickel in Germanium. As a matter of fact, the conclusions reached about the capture rates of this deep double acceptor center are not unanimous (see tab. 1). To my knowledge, there are three works offering a quite complete picture of the recombination coefficients, based on different experimental techniques, along with a number of studies giving one or two among the four capture rates. Klassen et al. (1961) obtains $\frac{K_2}{K_1} = 0.14 < 1$ by generation-recombination noise measurements, but Wertheim (1959), Tseng & Li (1972), and Eliseev & Kalashnikov (1963) obtain $\frac{K_2}{K_1} = 6 > 1$, with photoconductive methods. Wertheim and Tseng give three of the four coefficients necessary for the calculation of rel.40 (K_1 , K_2 , and R_2). Wertheim obtains $20 < R_2 < 80$, which could give bistability, according to rel.40 if $R_1 > 5$, that is: $\sigma_{1p} > 5 \times 10^{-16} \text{cm}^2$. This inequality is largely satisfied by the values of σ_{1p} independently obtained by all the other reserchers (see tab. 1) at sufficiently low temperatures. Tseng and Li, on the other hand, give a value of $R_2 \approx 5$, wich is slightly too small to permit bistability, also with very large values of R_1 . In conclusion, there is conclusive evidence, by fotoconductive measurements, that the necessary condition $K_2 > K_1$ is satisfied for Nickel in Germanium; moreover, there are suggestions that also the sufficient condition of rel. 40 is satisfied for this center, at least at low temperatures ($\approx 100\text{K}$).

A numerical simulation of the behavior of n-doped germanium, lightly compensated with Nickel, has been carried out, solving eqs. 33. The parameters were those given by Wertheim (1959), along with $\sigma_{1p} \equiv \sigma_{p-/0} = 10^{-13} \text{cm}^2$, which is a conservative estimate based on the values of tab. 1. The doping centers and the recombination centers concentrations were, respectively, $N = 10^{16} \text{cm}^{-3}$, $M = 5 \times 10^{14} \text{cm}^{-3}$. Figure 8 (left) represent the hysteresis cycle of the valence band population, as a function of the generation factor, and Fig.8 (right) represents the response of the valence band population to pulses above and below the bistable

Author method	$\sigma_{n-}/_0$ $\sigma_{n--}/-$ (10^{-16}cm^2)	Temperature	$\sigma_{p-}/_0$ $\sigma_{p--}/-$ (10^{-16}cm^2)	Temperature
(Wertheim, 1959) PC	0.96 5	indep. indep.	100 – 400	lowers with T
(Tseng & Li, 1972) PC	1.4 6.8	300K 300K	40	300K
(Klassen et al., 1961) GR Noise	17 2.3	300K	350 > 1000	$\sigma_{200\text{K}} \times T^{-1.5}$ 300 K
(Eliseev & Kalashnikov, 1963) PEM, PC, PC decay	0.5 3	300K indep. 300K indep.		
(Kalashnikov & Tissen, 1959) PC, PC decay	20	150-300K	200	150-300K
(Kotina et al., 1987) DLTS	180	105-125K	8800	95-110K
(Rupprecht, 1961) Pulsed Field			7000	$\sigma_{100\text{K}} \times T^{-(0.5-1)}$

Table 1. Capture cross sections for Nickel centers in Germanium, as measured by several authors. All the authors but Klaassen which measured $\sigma_{n-}/_0$ and $\sigma_{n--}/-$ give a ratio $\frac{\sigma_{n--}/-}{\sigma_{n-}/_0}$ of about 6, compatible with bistability.

interval. For the values of the parameters given above, bistability occurs for generation factors $g \approx 7.5 \times 10^{21} \text{cm}^{-3}\text{s}^{-1}$ which are obtained, for an over band-gap radiation with a penetration lenght of $100\mu\text{m}$, at a power density of about $8\text{W}/\text{cm}^2$. Transitions ON-OFF and OFF-ON occurs with pulses of at least $2\mu\text{s}$ of duration. The transition time and the power density, according to rel. 43 and 42, scale as $\frac{1}{M}$ and $N \times M$, respectively, which could give a slight freedom of choice in the bandgap engineering to achieve a bistable photoconducting behavior.

Fig. 8. (left) Hysteresis cycle of the valence band population, as a function of the generation factor, for *n*-doped germanium lightly compensated by nickel centers (parameters in section 7). (right) Response of the valence band population to pulses above and below the bistable interval.

If a photoconduction experiment is performed in the current regime (Bass et al., 1970), with a ballast resistance between the sample and a DC power supply, the bistability effect should be detected also with an electric field as low as 1Vcm^{-1} , measuring the voltage drop across the photoconductor. This electric field intensity is well below the limit for impact ionization of impurities in germanium (Kahn et al., 1992), and could not be mistaken with any avalanche-related bistability effect.

8. Conclusions

Instability in photoconduction is a long recognized issue, whose study, both experimental and theoretical, has been grounded on the basis of avalanche-related phenomena. This approach has been fruitful in term of comprehension of an amount of phenomena involved: spatial patternization, temporal behavior including chaotic oscillations in semiconductors has been deeply studied and accounted for. Nevertheless, other routes toward instability or multistability, potentially more reliable for the applications, has been neglected, in a way that none of the possible instability mechanisms in ionization-recombination processes, apart from those involving impact ionization, has been explored before the work exposed in this chapter. We have realized that, even without the intervention of any electric field, instability in photoconduction processes can occur due to competition between mutually interacting recombination channels, namely in case of deep recombination centers with metastable excited states and in the presence of multiple ionization of recombination impurities. Moreover, the variational analysis of the problem showed that these are the only two cases which admit recombination instability in absence of avalanche-related processes. Sufficient, close algebraic conditions on the recombination coefficients has been stated assuring bistability in this two cases, and some deep centers which are candidate to exhibit recombination bistability has been identified. Experimental work is worth doing, on one hand to obtain a deeper characterization of the recombination coefficients of the centers which are potential candidate to assure photoconductive bistability, on the other, to test the effective ability to trigger instability of the centers which, at the moment, seems to be the most promising candidates.

9. References

- Aoki, K. (2001). *Nonlinear Dynamics and Chaos in Semiconductors*, Institute of Physics Publishing, Bristol and Philadelphia.
- Bass, F., Bochov, V. & Gurevich, Y. G. (1970). *Sov. Phys. JEPT* 31: 972.
- Bel'kov, V. V., Hirschinger, J., Novak, V., F.-J. Niedernostheide, Ganichev, S. & Prettl, W. (1999). *Nature* 397, 4 February 1999: 398.
- Berman, A. & Plemmons, R. (1994). *Nonnegative Matrices in the Mathematical Sciences*, Society for Industrial and Applied Mathematics, Philadelphia.
- Bonch-Bruевич, V. L., Zvyagin, I. P. & Mironov, A. (1975). *Domain Electrical Instabilities in Semiconductors*, Consultants Bureau, New York.
- Brandl, A. & Prettl, W. (1991). *Phys. Rev. Lett.* 66: 3044.
- Crandal, R. (1970). *Phys. Rev.* 1 (2): 730–738.
- Delaye, P. & Sugg, B. (1994). Temperature enhancement of the photorefractive effect in GaAs due to the metastable state of the EL2 defect, *Phys. Rev. B* 50: 16973.
- Eliseev, P. & Kalashnikov, S. (1963). *Sov. Phys. Solid State* 5: 233.
- Frenkel, J. (1938). *Phys. Rev.* 54: 647.

- Ganichev, S. D., Raab, W., Zepezauer, E., Prettl, W. & Yassievich, I. N. (1997). Storage of electrons in shallow donor excited states of gap:te, *Phys. Rev. B* 55: 9243.
- Ghosh, A. K., Lauer, R. & Jr., R. A. (1973). Photoconductivity and photoluminescence kinetics associated with the luminescence center in rutile (tio₂), *Phys. Rev. B* 8: 4842.
- Golik, L., Gutman, M. M. & Pakseev, V. E. (1990). Nonlinear oscillations and chaos in cds single crystals under temperature-electric instability conditions, *phys. stat. sol. (b)* 199(162).
- Grillenberger (2004). *Phys. Rev. B* 70: 205209.
- Hearon, J. (1963). *Ann NY Acad Sci* 108: 36.
- Hirschinger, J., Niedernostheide, F.-J., W.Prettl & V.Novák (2000). *Phys. Rev. B* 61: 1952.
- Jelezko, F. & Wrachtrup, J. (2006). *phys. stat. sol. (a)*, *Unknown Journal* 203: 3207.
- Kahn, A. M., Mar, D. J. & Westervelt, R. M. (1992). Spatial measurements near the instability threshold in ultrapure ge, *Phys. Rev. B* 45: 8342.
- Kalashnikov, S. G. & Tissen, K. P. (1959). Unknown title, *Sov. Phys. Solid State* 1: 1603.
- K.Aoki & K.Yamamoto (1989). *Appl. Phys. A* 48: 111.
- Khosla, R., Fisher, J. & Burkey, B. (1973). *Phys. Rev. B* 7 (6): 2551–2564.
- Kim, C.-G. & Yung, Y.-D. (2004). *J. Appl. Phys.* 96 (1): 913.
- Klassen, F., Blok, J. & Booy, H. (1961). *Physica* 27: 48.
- Knack, S., Weber, J., Lemke, H. & Riemann, H. (2002). *Phys. Rev. B* 65: 165203.
- Koenig, S. (1958). *Phys. Rev.* 110: 986–988.
- Koepp, R. & Urbelis, A. (1968). Low frequency photocurrent oscillations in cds crystals with thermally induced negative differential conductivity, *Phys. stat. sol.* 30: K5.
- Kotina, I., Kuryatkov, V., Novikov, S. & Pirozhkova, I. (1987). Unknown title, *Sov. Phys. Semicond.* 21: 635.
- Lagomarsino, S. (2007). Instability in nonautocatalytic ionization-recombination processes, *Phys. Rev. B* 75: 024305.
- Lagomarsino, S. (2008). Optoelectronic bistability effect in semiconductors, *Phys. Rev. B* 78: 125201.
- Landsberg, P. & Pimpale, A. (1976). *J. Phys. C* 9: 1243–1251.
- Lin, A. L., Omelianovski, E. & Bube, R. H. (2006). Photoelectronic properties of high-resistivity gaas:o, *Journal of Applied physics* 47(1852).
- Lorentz, E. (1963). *Journal of the atmospheric sciences* 20: 130–141.
- Mcwhorter, A. & Rediker, R. (1959). *Proceedings of the IRE* 47: 1207–1213.
- Menoret, M. (1968). *U.S. PATENT* 3404383.
- Minorsky, N. (1962). *Nonlinear Oscillations*, D. Van Nostrand Company, Inc., Princeton, New Jersey.
- Pagonis, V., C.Ankjærgaard, A.S.Murray, M.Jain, R.Chen, J.Lawless & S.Greilich (2010). Modelling the thermal quenching mechanism in quartz based on time-resolved optically stimulated luminescence, *Journal of luminescence* 130: 902.
- Reggiani, L. & Mitin, V. (1989). *Rev. Nuov. Cim.* 12: 1.
- Roessler, O. (1976). *Phys. Lett.* 57A: 397.
- Rupprecht, G. (1961). Unknown title, *J. Phys. Chem. Solids* 22: 255.
- Sachse, J.-U., Weber, J. & Lemke, H. (2000). *Phys. Rev. B* 61: 1924.
- Schöll, E. (1979). *Proc. R. Soc. Lond. A* 365: 511–521.
- Schöll, E. (1982). *Z. Phys. B* 46: 23–30.
- Schöll, E. (1987). *Nonequilibrium Phase Transitions in Semiconductors - Self-organization Induced by Generation and Recombination Processes*, Springer, Berlin.

- Shiraishi, M., Sachse, J.-U., Lemke, H. & Weber, J. (1999). *Material Science and Engineering* B58: 130.
- Stobbe, M., Redmer, R. & Schattke, W. (1994). *Phys. Rev. B* 49 (7): 4494.
- Sudzius, M., Bastys, A. & Jarasiunas, K. (1999). Optical nonlinearities at transient quenching of el2 defect at room temperature, *Optics Communications* 170: 149.
- Todd, J. (1962). *Survey of Numerical Analysis*, McGraw-Hill Book Company, Inc., New York.
- Tseng, H. F. & Li, S. S. (1972). *Phys. Rev. B* 6 (8): 3066.
- Vincent, G., Bois, D. & Chantre, A. (1982). Photoelectric memory effect in gaas, *Journal of Applied Physics* 53: 3643.
- Wertheim, G. (1959). *Phys. Rev.* 115: 37.
- Yarykin, N., Sachse, J.-U., Lemke, H. & Weber, J. (1999). *Phys. Rev. B* 59: 5551.
- Yoffa, E. (1981). *Phys. Rev. B* 23 (4): 1909.

IntechOpen

Optoelectronic Devices and Properties

Edited by Prof. Oleg Sergiyenko

ISBN 978-953-307-204-3

Hard cover, 660 pages

Publisher InTech

Published online 19, April, 2011

Published in print edition April, 2011

Optoelectronic devices impact many areas of society, from simple household appliances and multimedia systems to communications, computing, spatial scanning, optical monitoring, 3D measurements and medical instruments. This is the most complete book about optoelectromechanic systems and semiconductor optoelectronic devices; it provides an accessible, well-organized overview of optoelectronic devices and properties that emphasizes basic principles.

How to reference

In order to correctly reference this scholarly work, feel free to copy and paste the following:

Stefano Lagomarsino (2011). Bistable Photoconduction in Semiconductors, Optoelectronic Devices and Properties, Prof. Oleg Sergiyenko (Ed.), ISBN: 978-953-307-204-3, InTech, Available from: <http://www.intechopen.com/books/optoelectronic-devices-and-properties/bistable-photoconduction-in-semiconductors>

INTECH
open science | open minds

InTech Europe

University Campus STeP Ri
Slavka Krautzeka 83/A
51000 Rijeka, Croatia
Phone: +385 (51) 770 447
Fax: +385 (51) 686 166
www.intechopen.com

InTech China

Unit 405, Office Block, Hotel Equatorial Shanghai
No.65, Yan An Road (West), Shanghai, 200040, China
中国上海市延安西路65号上海国际贵都大饭店办公楼405单元
Phone: +86-21-62489820
Fax: +86-21-62489821

© 2011 The Author(s). Licensee IntechOpen. This chapter is distributed under the terms of the [Creative Commons Attribution-NonCommercial-ShareAlike-3.0 License](https://creativecommons.org/licenses/by-nc-sa/3.0/), which permits use, distribution and reproduction for non-commercial purposes, provided the original is properly cited and derivative works building on this content are distributed under the same license.

IntechOpen

IntechOpen