

We are IntechOpen, the world's leading publisher of Open Access books Built by scientists, for scientists

6,900

Open access books available

185,000

International authors and editors

200M

Downloads

Our authors are among the

154

Countries delivered to

TOP 1%

most cited scientists

12.2%

Contributors from top 500 universities



WEB OF SCIENCE™

Selection of our books indexed in the Book Citation Index
in Web of Science™ Core Collection (BKCI)

Interested in publishing with us?
Contact book.department@intechopen.com

Numbers displayed above are based on latest data collected.
For more information visit www.intechopen.com



Analysis of Power Electronic Controllers in Electric Power Systems Using Simulink

Juan Segundo-Ramirez¹ and A. Medina²

¹*Universidad Autónoma de San Luis Potosí*

²*Universidad Michoacana de San Nicolás de Hidalgo*
México

1. Introduction

Flexible ac Transmission Systems (FACTS) devices have emerged in power system because of the development of power electronics components for high voltage and power. The FACTS devices provide higher controllability in power systems by means of power electronic devices. Several FACTS equipments have been already introduced for various applications worldwide, and new types of FACTS are in the stage of being introduced in practice. FACTS technology provides a better ability to varying operational conditions and improves the usage of existing installations.

2. Power electronic application in transmission systems

It can be seen that with growing line length and with higher power demand the opportunity for FACTS devices gets more important. The devices work electrically as fast current, voltage or impedance controllers. The power electronic allows very short reaction times down to far below one second (\sim ms). Detailed introductions in FACTS devices can also be found in the literature (Hingorani & Gyudyi, 2000) (Acha, et al. 2004) (Mathur & Varma, 2002)(Padiyar, 2007) (Zhang, Rehtanz, & Pal, 2006) with the main focus on new topologies, modeling and control.

Basically, there are two groups of FACTS, one is based on thyristor valve operation (Hingorani & Gyudyi, 2000), and the other is based on Voltage Source Converters (VSCs) (Segundo-Ramírez & Medina, 2008) (Segundo-Ramírez & Medina, 2009). A list of some FACTS devices are shown in Table 1. The FACTS devices based on VSCs provide a controllable voltage magnitude and phase angle due to a Pulse Width Modulation (PWM) technique (Mohan, Underland, & Robins, 1995). The Static Compensator (STATCOM) (Hingorani & Gyudyi, 2000) is a shunt connected device that is able to provide reactive power support at a network location far away from the generators. Through this reactive power injection, the STATCOM can regulate the voltage at the connection node. The Static Synchronous Series compensator (SSSC) (Hingorani & Gyudyi, 2000) is a series device which injects a voltage in series with the transmission line. The Unified Power Flow Controller (UPFC) (Hingorani & Gyudyi, 2000) is the most versatile device of the family of FACTS devices, since it is able to control the active and the reactive power, respectively, as

well as the voltage at the connection node. In Figure 1 a schematic representation of the STATCOM, the SSSC, and the UPFC are presented. The compensating FACTS devices under analysis in this chapter are briefly described below.

Connection Type	FACTS Devices	
	Thyristor-Based FACTS	VSC-Based FACTS
Shunt Connected	Static Var Compensator (SVC)	Static Compensator (STATCOM)
Series Connected	Thyristor Controlled Series Compensator (TCSC)	Static Series Synchronous Compensator (SSSC)
Back-to-Back Connected	HVDC	Unified Power Flow Controller (UPFC)
		HVDC VSC

Table 1. Overview of the principal FACTS-Devices.




Fig. 1. FACTS devices based on VSCs. (a) STATCOM, (b) SSSC, and (c) UPFC.

2.1 Static compensator (STATCOM)

It is a shunt device that does not require passive elements for reactive compensation. The STATCOM operation is based on a VSC, which is supplied by a dc storage capacitor. The VSC terminals are connected to the dc system through a coupling transformer. The VSC produces a quasi-sine wave voltage at the fundamental frequency (50 or 60 Hz). The STATCOM can generate or absorb reactive power. A schematic representation of the STATCOM is shown in Figure 1(a).

Assuming that the losses in the VSC and the coupling transformer are negligible, $v_{statcom}$ is in phase with the voltage at the terminal bus v_k . In this situation, the current $i_{statcom}$ is completely reactive. If the magnitude of the voltage v_k is higher than the magnitude of $v_{statcom}$, the reactive current flows from the bus to the VSC, which means that the STATCOM absorbs reactive power. On the other hand, if the magnitude of $v_{statcom}$ is higher than the magnitude of v_k , the reactive current flows from the VSC to the ac system. Then, the STATCOM injects reactive power to the system. In practice, the power losses of the STATCOM are not negligible and must be drawn from the ac system to maintain constant the dc capacitor voltage.

2.2 Static synchronous series compensator (SSSC)

The SSSC is a series device in which a synchronous voltage source injects a fundamental frequency voltage in series with the transmission line through a coupling transformer. The synchronous voltage source is supplied by a VSC. A schematic representation of the SSSC is shown in Figure 1(b).

Ideally, the injected voltage is in quadrature with the line current. In this mode the VSC does not absorb or inject any real power. However, in practice, the VSC losses must be replenished by the ac system, in consequence a small phase lag is introduced for this purpose. The operating characteristics make this device very attractive for power transmission application. The main limitation of application is due to the losses and cost of the converter. The SSSC is a device which has so far not been built at transmission level because Series Compensator (fixed capacitor) and thyristor controlled series capacitor (TCSC) (Hingorani & Gyudyi, 2000) are fulfilling all the today's operational requirements at a low cost.

2.3 Unified power flow controller (UPFC)

This device contains two VSCs connected together through a dc link storage capacitor. One of the VSCs is connected in series with the transmission line, while the other VSC is connected in shunt with the transmission line. The UPFC can control the active and reactive power flow in the transmission line, and at the same time can regulate the voltage magnitude at the connection node. To control the real and reactive power flow in the series side, the UPFC allows interchange of real power between the shunt and the series converters. The main disadvantage of this device is the high cost level due to the complex systems setup (Zhang, Rehtanz, & Pal, 2006). A schematic representation of the UPFC is shown in Figure 1(c).

3. PSB/SIMULINK

Power System Blockset (PSB) for use with Matlab/Simulink employs state-variable analysis. In PSB complex control algorithms can be implemented into the models in an easy and fast way. Besides, PSB can use several Matlab toolboxes. In particular, it has the PWM generator and the VSC blocks. The main advantage of the PSB is that it is developed in Matlab/Simulink environment, this fact makes possible to use it together with several other control design tools. It is possible to use the Simulink Accelerator and the Real-Time Workshop to improve the PSB performance; a C code is generated. Additionally, the PSB can use several integration methods, which make it a powerful simulation tool.

3.1 Modeling and analysis of FACTS by PSB/SIMULINK

This section is divided into three parts. Simulations relating to the STATCOM are presented first. This is followed by simulations carried out for the SSSC and then for the UPFC. The study case related to the STATCOM is described in detail using PSB/Simulink. For the cases of the SSSC and the UPFC, only the general implementation is described.

peak line-to-neutral voltage at the bus 1 is shown in Figure 5(d). Figure 6 shows the steady state waveform of the voltage at the bus 1 at the top of the figure, and its harmonic spectrum at the bottom of the figure. The Figure 6 was obtained using the FFT Analysis button in the powergui block.

In the Figure 7, some selected transient waveforms of the STATCOM with the passive filter are shown: Figure 7(a) presents the output of the phase controller; Figure 7(b) presents the output of the magnitude control; Figure 7(c) shows the voltage across the dc capacitor, and finally, the peak line-to-neutral voltage at the bus 1 is shown in Figure 7(d). Figure 8 shows the steady state waveform of the voltage at the bus 1 at the top of the figure, and its harmonic spectrum at the bottom of the figure.




Fig. 3. STATCOM PI control system. (a) Main control system. (b) Bandpass filter. (c) Extraction of the peak value of a three-phase voltage in abc-reference.




Fig. 4. Blocks parameters of important components.




Fig. 5. Selected transient waveforms of the STATCOM without passive filter. (a) Phase angle of the voltage at the ac terminals of the VSC. (b) Amplitude modulation ratio. (c) Voltage across the dc capacitor. (d) Peak line-to-neutral voltage at the bus 1.

From Figure 5 and Figure 7 it is easy to notice that the passive filter has a positive impact on the reduction of the harmonic distortion in the power network without affecting the performance of the controller. In Figure 6, the waveform of the voltage at bus 1 is severely distorted with a total harmonic distortion (THD) of 39.88%. In this case, some harmonic components have a magnitude of almost 20% of the fundamental component, which is an undesirable operating condition in practical applications. On the other hand, the obtained voltage at bus 1 when the passive filter is on has a THD of 4.23% and the highest magnitude of the harmonic components is around 3.5% of the fundamental component, as shown in Figure 8.

In this simulation analysis, a discrete representation of the system given in Figure 2 was used in order to carry-out the simulations, an integration step of $1\ \mu\text{s}$ was selected.




Fig. 6. Steady state waveform of the voltage at the bus 1 without passive filter (top), and its harmonic spectrum (bottom).




Fig. 7. Selected transient waveforms of the STATCOM with passive filter. (a) Phase angle of the voltage at the ac terminals of the VSC. (b) Amplitude modulation ratio. (c) Voltage across the dc capacitor. (d) Peak line-to-neutral voltage at the bus 1.




Fig. 8. Steady state waveform of the voltage at the bus 1 with passive filter (top), and its harmonic spectrum (bottom).

3.2.1 Static synchronous series compensator (SSSC)

The test system for the analysis of the SSSC is shown in Figure 9. The network parameters are the same of those of Figure 2. The series transformers are represented b an ideal model. The series active power reference P_{ref} in the line 2 is equal to 5500 W; the dc voltage capacitor reference is equal to 500 V; the gains of the power control are $K_p=0.000015$ and $K_i=0.004$, and its limits are 0 and 1; the gains of the dc voltage control are $K_p=0.03$ and $K_i=1$, and its limits are $-\pi$ and π

The SSSC includes the control system shown in Figure 10. This control has two control objectives: to control the active power (P) that flows in the transmission line connected in series with the SSSC, and to maintain the dc voltage capacitor at its reference value. Remember that the SSSC does not interchange active power in steady-state, only the power loss; otherwise the dc capacitor is discharged. In transient state the SSSC has transient interchanges of active power with the network, which is reflected in variation of the dc voltage. Under this situation, the control regulates the interchange of active power in order to maintain the dc voltage capacitor at its steady-state. The initial




Fig. 10. SSSC control.




Fig. 11. Selected transient waveforms of the SSSC without passive filter. (Top left) Series active power. (Top right) Amplitude modulation ratio. (Bottom left) Voltage across the dc capacitor. (Bottom right) Phase angle of the voltage at the ac terminals.

Figure 12 shows the steady state waveform of the voltage at bus 1 without passive filter. In this operating scenario, the voltage is highly distorted; the THD is around 22.85% and the harmonics 39 and 43 have a magnitude of around 12% of the fundamental component. Notice that THD is high even when the switching frequency is 2.46 kHz. On the other hand, of some selected variables, the transient and steady state solutions of the SSSC test system including the passive filter are shown in Figure 13 and Figure 14. Comparing Figure 11 and Figure 13, it is easy to notice that difference between these figures is negligible. The most remarkable difference is the reduction of the harmonic distortion in all the system, especially in the voltage at bus 1.




Fig. 12. Steady state waveform of the voltage at the bus 1 without passive filter (top), and its harmonic spectrum (bottom).




Fig. 13. Selected transient waveforms of the SSSC with passive filter. (Top left) Series active power. (Top right) Amplitude modulation ratio. (Bottom left) Voltage across the dc capacitor. (Bottom right) Phase angle of the voltage at the ac terminals.




Fig. 14. Steady state waveform of the voltage at the bus 1 with passive filter (top), and its harmonic spectrum (bottom).

3.2.2 Unified power flow controller (UPFC)

The UPFC test system of Figure 15 and Figure 16 shows the Simulink implementation of the UPFC. The network parameters are the same of those of Figure 2. The UPFC including the shunt control described in (Mahyavanshi & Radman, 2006) is schematically shown in Figure 18, and the series control proposed in (Fujita, Watanabe, & Akagi, 2001) is shown in Figure 17. The initial condition is zero, except for the dc capacitor voltage, which is 500 volts.

The series controller regulates the real ($P_{ref}=8500$ watts) and reactive ($Q_{ref}=0$ vars) power flows by adjusting the injected series voltage. The shunt converter regulates the voltage across the dc capacitor and the sending end voltage V1 at bus 1. The modulation index is $m_f=27$, which represents a commutation frequency of 1.61 kHz. The RC passive filter has a capacitance of $80\text{ }\mu F$ and a resistance of $0.2\text{ }\Omega$. The gains for the series controller are the following: $K_p=1$ and $K_i=500$ for the Discrete PI Controller 1, with no limits; $K_p=2$ and $K_i=1000$ for the Discrete PI Controller 2, with no limits. On the other hand, the gains for the shunt controller are: $K_p=0.002$ and $K_i=1$ for the Discrete PI Controller 1, with no limits; finally, $K_p=0.0012$ and $K_i=0.09$ for the Discrete PI Controller 2, with no limits. The UPFC analysis presented in this section only includes the case when the passive filter is connected, as shown in Figure 15.




Fig. 15. Test system including the UPFC.

The dynamic response of UPFC controllers are presented in Figure 19. From this figure, it is possible to observe that the variation of the three-phase programmable voltage source significantly affects the response of the series controller. This is because the magnitude of the voltages at the ends of the line controlled by the UPFC affects the power flow across the line. On the other hand, Figure 20 shows the transient waveform of the voltage across the dc capacitor and the active and reactive power flow in the controlled line. Notice that the reactive and active power remains close to the reference during the step changes in the three-phase programmable voltage source. Finally, Figure 21 presents the periodic steady-state solution of the sending end voltage V1 and its harmonic spectrum, which has a low THD of 1.74%.




Fig. 18. Shunt controller.




Fig. 19. Transient response of the series and shunt controllers of UPFC.




Fig. 20. Transient waveforms of selected variables: (Left) Voltage across the dc capacitor. (Right) Reactive (purple) and active (yellow) power.




Fig. 21. Steady state waveform of the voltage at the bus 1 (top) and its harmonic spectrum (bottom).

4. Conclusions


In this chapter, implementation in Simulink of three FACTS devices based on VSC has been presented. These implementations include the STATCOM, SSSC, and the UPFC. All the implementations have been carried-out taking into account the control systems. The presented models can be used in order to analyze the dynamic and the periodic steady-state behavior of these FACTS components.

5. Acknowledgements

The authors thank the Univesidad Autónoma de San Luis Potosí (UASLP) and the Universidad Michoacana de San Nicolás de Hidalgo (UMSNH) for the facilities that were granted to carry out this chapter.

6. References

- Acha, E., Fuerte-Esquivel, C., Ambriz-Pérez, H., & Angeles-Camacho, C. (2004). *FACTS Modelling and Simulation in Power Networks*, John Wiley & Sons, 9780470852712, England
- Fujita, H., Watanabe, Y., & Akagi, H. (2001). Transient Analisis of a Unified Power Flow Controller and its Application to Design of the DC-Link Capacitor. *IEEE Transaction on Power Electronics*, Vol. 16, No. 5, (september 2001), pp. 735-740, 0885-8993
- Hingorani, N. G., & Gyudyi, L. (2000). *Undestanding FACTS*, IEEE Press, 078033455, New York
- Mahyavanshi, B., & Radman, G. (2006). A Study of Interaction Between Dynamic Load and STATCOM. *Proceedings of the 38th southeastern symposium on system theory*, 0-7803-9457-7, Cookeville, TN, march 2006
- Mathur, R., & Varma, R. (2002). *Thyristor Based FACTS Controllers for Electrical Transmission Systems*, IEEE Computer Society Press, ISSN, Piscataway, New Jersey
- Mohan, N., Underland, T. M., & Robins, W. P. (1995). *Power Electronics: Converters, Applications, and Design*, Wiley, 0471226939, New York
- Padiyar, K. R. (2007). *FACTS Controller in Power Transmission and Distribution*, New Age, 978-81-224-2142-2, New Delhi
- Segundo-Ramírez, J., & Medina, A. (2009). Modeling of FACTS Devices Based on SPWM VSCs. *IEEE Transaction on Power Delivery*, Vol. 24, No. 4, (November 2009), pp. 1815-1823, 0885-8977
- Segundo-Ramírez, J., & Medina, A. (2008). Periodic Steady-State Solution of Electric Systems Including UPFCs by Extrapolation to the Limit Cycle. *IEEE Transaction on Power Delivery*, Vol. 23, No. 3, pp. 1506-1512
- Zhang, X.-P., Rehtanz, C., & Pal, B. (2006). *Flexible AC Transmission Systems: Modelling and Control*, Springer-Verlag. 978-3-540-30606-1, Germany



Technology and Engineering Applications of Simulink

Edited by Prof. Subhas Chakravarty

ISBN 978-953-51-0635-7

Hard cover, 256 pages

Publisher InTech

Published online 23, May, 2012

Published in print edition May, 2012

Building on MATLAB (the language of technical computing), Simulink provides a platform for engineers to plan, model, design, simulate, test and implement complex electromechanical, dynamic control, signal processing and communication systems. Simulink-Matlab combination is very useful for developing algorithms, GUI assisted creation of block diagrams and realisation of interactive simulation based designs. The eleven chapters of the book demonstrate the power and capabilities of Simulink to solve engineering problems with varied degree of complexity in the virtual environment.

How to reference

In order to correctly reference this scholarly work, feel free to copy and paste the following:

Juan Segundo-Ramirez and A. Medina (2012). Analysis of Power Electronic Controllers in Electric Power Systems Using Simulink, Technology and Engineering Applications of Simulink, Prof. Subhas Chakravarty (Ed.), ISBN: 978-953-51-0635-7, InTech, Available from: <http://www.intechopen.com/books/technology-and-engineering-applications-of-simulink/analysis-of-power-electronic-controllers-in-electric-power-systems-using-simulink>

INTECH
open science | open minds

InTech Europe

University Campus STeP Ri
Slavka Krautzeka 83/A
51000 Rijeka, Croatia
Phone: +385 (51) 770 447
Fax: +385 (51) 686 166
www.intechopen.com

InTech China

Unit 405, Office Block, Hotel Equatorial Shanghai
No.65, Yan An Road (West), Shanghai, 200040, China
中国上海市延安西路65号上海国际贵都大饭店办公楼405单元
Phone: +86-21-62489820
Fax: +86-21-62489821

© 2012 The Author(s). Licensee IntechOpen. This is an open access article distributed under the terms of the [Creative Commons Attribution 3.0 License](#), which permits unrestricted use, distribution, and reproduction in any medium, provided the original work is properly cited.

IntechOpen

IntechOpen